

Critical Slowing-Down in $SU(2)$ Landau-Gauge-Fixing Algorithms at $\beta = \infty$

Attilio Cucchieri and Tereza Mendes

IFSC-USP, Caixa Postal 369

13560-970 São Carlos, SP, Brazil

E-mail: attilio@if.sc.usp.br, mendes@if.sc.usp.br

February 1, 2008

Abstract

We evaluate numerically and analytically the dynamic critical exponent z for five gauge-fixing algorithms in $SU(2)$ lattice Landau-gauge theory by considering the case $\beta = \infty$. Numerical data are obtained in two, three and four dimensions. Results are in agreement with those obtained previously at finite β in two dimensions. The theoretical analysis, valid for any dimension d , helps us clarify the tuning of these algorithms. We also study generalizations of the overrelaxation algorithm and of the stochastic overrelaxation algorithm and verify that we cannot have a dynamic critical exponent z smaller than 1 with these local algorithms. Finally, the analytic approach is applied to the so-called λ -gauges, again at $\beta = \infty$, and verified numerically for the two-dimensional case.

1 Introduction

Lattice gauge fixing is a necessary step in our understanding of the relationship between continuum and lattice models. In fact, the continuum limit is the weak-coupling limit and a weak-coupling expansion requires gauge fixing. Thus, even though gauge fixing is in principle not needed for the lattice formulation of QCD, one is led to consider gauge-dependent quantities on the lattice as well, such as gluon, ghost and quark propagators, vertices, etc. [1]. It is therefore important to devise numerical algorithms to gauge-fix a lattice configuration efficiently. The main issue regarding the efficiency of these algorithms is the problem of *critical slowing-down* (CSD), which occurs when the relaxation time of an algorithm diverges as the lattice volume is increased (see for example [2, 3]). Besides the problem of CSD, we are also interested in understanding which quantities should be used to test the convergence of the gauge fixing and in finding prescriptions for the tuning of parameters in the algorithms, when tuning is needed.

In Ref. [4] we have studied the problem of critical slowing-down for five gauge-fixing algorithms in $SU(2)$ lattice Landau-gauge theory on two-dimensional lattices with periodic boundary conditions. We obtained that the local method called *Los Alamos* has *dynamic critical exponent* $z \approx 2$, the three improved local methods we considered — the *overrelaxation* method, the *stochastic overrelaxation* method and the so-called *Cornell* method — have critical exponent $z \approx 1$, and the global method of *Fourier acceleration* completely eliminates critical slowing-down. All these methods, except for the Los Alamos method, involve tuning. In that reference we also reported a detailed discussion and analysis of the tuning for the overrelaxation, the stochastic overrelaxation and the Cornell methods, and we made a comparative study of several quantities usually employed in the literature to check the convergence of the gauge fixing.

Here we redo that analysis for the case $\beta = \infty$, which can be studied analytically, and we include test runs in two, three and four dimensions¹. Let us recall the numerical problem we want to study: for a given (i.e. fixed) lattice configuration $\{U_\mu(x)\}$, we look for a gauge transformation $\{g(x)\}$ that brings the functional

$$\mathcal{E}_U[g] \equiv 1 - \frac{1}{dV} \sum_{\mu=1}^d \sum_x \frac{\text{Tr}}{2} \left[U_\mu^{(g)}(x) \right] \quad (1.1)$$

$$\equiv 1 - \frac{1}{dV} \sum_{\mu=1}^d \sum_x \frac{\text{Tr}}{2} \left[g(x) U_\mu(x) g^\dagger(x + e_\mu) \right] \quad (1.2)$$

$$= 1 - \frac{1}{dV} \sum_{\mu=1}^d \sum_x \frac{\text{Tr}}{2} \left[U_\mu(x) g^\dagger(x + e_\mu) g(x) \right] \quad (1.3)$$

to a local minimum, starting from a randomly chosen configuration $\{g(x)\}$. Here, x (with coordinates $x_\mu = 1, 2, \dots, N$) are sites on a d -dimensional lattice with periodic boundary conditions, $V = N^d$ is the lattice volume² and $U_\mu(x)$ and $g(x)$ are $SU(2)$ matrices. In order to analyze the CSD of an algorithm we have to investigate if, and with what exponent, its *relaxation time* τ diverges as the lattice size increases. To this end, we have to evaluate τ for different lattice sides N at “constant physics”, namely as the lattice size is increased, the *physical size* of the lattice should remain fixed. This is done by introducing a *correlation length* ξ and by keeping the ratio N/ξ constant. The lattice configuration $\{U_\mu(x)\}$ is usually chosen in equilibrium with

¹ Partial results can be found in [5].

² In order to simplify the notation we don't consider asymmetric lattices.

the Gibbs weight $\exp(-S[\beta, U])$, where $S[\beta, U]$ is the standard Wilson action in d dimensions. Since $S[\beta, U]$ depends only on the coupling β and on the lattice side N , we must change β and N in such a way that the pairs (β, N) correspond to the same value of N/ξ . For example — in two dimensions and for $\xi \equiv 1/\sqrt{\kappa}$, where κ is the *string tension* — $\xi(\beta, N)$ is known in the infinite-volume limit [6] and for large β we have the simple relation $\xi(\beta, \infty) \propto \beta^{1/2}$. [In Ref. [4] we considered different pairs (β, N) with the ratio N^2/β fixed and equal to 32, which corresponds to $N/\xi \approx 7$.] Of course, if the function $\xi(\beta, N)$ is not available, one should evaluate directly (i.e. numerically) the correlation length ξ , and tune β and N so that the ratio N/ξ is kept (approximately) fixed.

Since we are interested in studying gauge-fixing algorithms, i.e. minimizing the functional (1.2) for a given lattice configuration $\{U_\mu(x)\}$, a simpler possibility [7] is to work with lattices at $\beta = \infty$. This corresponds to using the Gibbs weight $\prod_{x,\mu} \delta(\mathbb{1} - U_\mu(x))$, namely the lattice configuration is completely ordered. In this case, the string tension κ is zero for any lattice side N , and therefore $N/\xi = N\sqrt{\kappa}$ is constant and equal to zero for all the pairs $(\beta = \infty, N)$. Note that with this particular choice the link variables $U_\mu(x)$ are set to $\mathbb{1}$ and the configuration $\{g(x)\}$ is chosen randomly. Thus, $U_\mu^{(g)}(x)$ is a pure gauge configuration, i.e. $U_\mu^{(g)}(x) = g(x) g^{-1}(x + e_\mu)$, which should be driven by the gauge fixing to the *vacuum* configuration $U_\mu^{(g)}(x) = \mathbb{1}$. As we will see in Section 3, the advantage of using this particular case — for which we know the final gauge-fixed configuration — is that we can study analytically the efficiency of the gauge-fixing algorithms.

In Section 2 we briefly review the five gauge-fixing algorithms considered in Ref. [4]. The case $\beta = \infty$ is studied analytically for general dimension d in Sections 3, 4 and 5 and the results are checked numerically in two, three and in four dimensions in Section 6. The analytic approach (see Section 3) is done by mapping — in the limit of large number of gauge-fixing sweeps t — the original problem (1.2) into the minimization of the action of a three-vector massless-free-field model [see eq. (3.6)]. In this way we obtain that the Cornell method coincides with the overrelaxation method, in agreement with the result found in Ref. [4], and we show that the Fourier acceleration method can eliminate critical slowing-down completely. In Section 4 we review the analysis of CSD done in Refs. [8, 9] for the thermalization of the Gaussian model and we apply it to the four local gauge-fixing algorithms considered here. This analysis confirms the results obtained in Ref. [4] and will give us a better understanding of the tuning for the three improved local algorithms. Moreover, in Section 5, we study generalizations of the overrelaxation algorithm and of the stochastic overrelaxation algorithm and check that we cannot have a dynamic critical exponent z smaller than 1 with these local algorithms. Note that this result applies directly to the problem of thermalizing a massless free field [8, 9, 10]. Finally, the analytic approach is extended to the so-called λ gauges (see for example [11]) in Section 7 and the results are verified numerically in the two-dimensional case.

Let us remark that the case $\beta = \infty$ gives information valid also for the algorithms at finite β . In fact, for each algorithm and “constant physics”, the evaluated relaxation times should be fitted by a function of the type

$$\tau = c N^z, \quad (1.4)$$

where the dynamic critical exponent z **should not** depend on the constant physics, i.e. it should be the same³ at finite β and at $\beta = \infty$. On the contrary, the constant c **should** depend on the

³ Of course, if the system undergoes a phase transition going from $\beta = 0$ to $\beta = \infty$, then an algorithm can

ratio N/ξ . In particular, for each algorithm, we should find a faster convergence of the gauge-fixing procedure — and therefore a smaller constant c — when the configuration $U_\mu(x)$ is less disordered, i.e. for larger values of β . This implies

$$c(\beta = \infty) < c(\text{finite } \beta) . \quad (1.5)$$

In Section 8 we check this inequality in two dimensions using the data obtained in Ref. [4] at finite β and the data produced for the present work. In the same section we also give our final comments and conclusions.

2 Gauge-Fixing Algorithms

In this Section we review briefly the five gauge-fixing algorithms we want to study, i.e. the so-called *Los Alamos* method, the *overrelaxation* method, the *stochastic overrelaxation* method, the so-called *Cornell* method and the *Fourier acceleration* method. To this end, let us recall that the updated gauge transformation at each step of the algorithm can be written for the four local methods as follows⁴

$$g^{(LosAl.)}(x) \equiv \tilde{h}^\dagger(x) \quad (2.1)$$

$$g^{(cornell)}(x) \equiv \frac{\alpha \mathcal{N}(x) \tilde{h}^\dagger(x) + [1 - \alpha \mathcal{N}(x) \mathcal{T}(x)/2] g(x)}{\sqrt{1 + \alpha^2 \mathcal{N}^2(x) [1 - \mathcal{T}^2(x)/4]}} \quad (2.2)$$

$$g^{(over)}(x) \equiv \frac{\omega \tilde{h}^\dagger(x) + (1 - \omega) g(x)}{\sqrt{1 + \omega(\omega - 1) [2 - \mathcal{T}(x)]}} \quad (2.3)$$

$$g^{(stoc)}(x) \equiv \begin{cases} \tilde{h}^\dagger(x) \mathcal{T}(x) - g(x) & \text{with probability } p \\ \tilde{h}^\dagger(x) & \text{with probability } 1 - p \end{cases} . \quad (2.4)$$

Notice that, with the exception of the Los Alamos method, all the above algorithms have a tuning parameter, i.e. α for the Cornell method, ω for the overrelaxation algorithm and p for the stochastic overrelaxation algorithm. Also, in eqs. (2.1)–(2.4) we have used the definition

$$h(x) \equiv \sum_{\mu=1}^d \left[U_\mu(x) g^\dagger(x + e_\mu) + U_\mu^\dagger(x - e_\mu) g^\dagger(x - e_\mu) \right] \quad (2.5)$$

and the fact that the matrix $h(x)$ is proportional to an $SU(2)$ matrix, namely it can be written as

$$h(x) \equiv \mathcal{N}(x) \tilde{h}(x) \quad (2.6)$$

with $\tilde{h}(x) \in SU(2)$ and

$$\mathcal{N}(x) = \sqrt{\det h(x)} = \sqrt{\frac{\text{Tr}}{2} h(x) h^\dagger(x)} . \quad (2.7)$$

show a different behavior in different phases (see for example Ref. [12]).

⁴ See Ref. [4] for more details.

We also define

$$\mathbf{w}(x) \equiv g(x) h(x) \quad (2.8)$$

and

$$\mathcal{T}(x) = \frac{1}{\mathcal{N}(x)} \text{Tr } \mathbf{w}(x) . \quad (2.9)$$

Using the definition of $U_\mu^{(g)}(x)$ [see eq. (1.2)] and eq. (2.5) one can check that

$$\mathbf{w}(x) = \sum_{\mu=1}^d \left[U_\mu^{(g)}(x) + U_\mu^{(g)\dagger}(x - e_\mu) \right] . \quad (2.10)$$

For the Fourier acceleration algorithm one usually writes [4]

$$g^{(Fourier)}(x) \propto \left\{ \mathbb{1} - \alpha \left[\hat{F}^{-1} \frac{1}{p^2(k)} \hat{F} (\nabla \cdot A^{(g)}) \right] (x) \right\} g(x) , \quad (2.11)$$

where α is a tuning parameter, $\mathbb{1}$ is the identity matrix, $\hat{F}$ indicates the Fourier transform, $\hat{F}^{-1}$ is its inverse,

$$(\nabla \cdot A^{(g)})(x) \equiv \sum_{\mu=1}^d A_\mu^{(g)}(x) - A_\mu^{(g)}(x - e_\mu) \quad (2.12)$$

is the lattice divergence of the (gauge-transformed) gauge field

$$A_\mu^{(g)}(x) \equiv \frac{1}{2} \left[U_\mu^{(g)}(x) - U_\mu^{(g)\dagger}(x) \right] \quad (2.13)$$

and

$$p^2(k) \equiv 4 \sum_{\mu=1}^d \sin^2 \left(\frac{p_\mu}{2} \right) \equiv 4 \sum_{\mu=1}^d \sin^2 (\pi k_\mu) \quad (2.14)$$

is the squared magnitude of the lattice momentum. The vector k has components k_μ ($\mu = 1, \dots, d$) given by $k_\mu N = 0, 1, \dots, N-1$, where N is the lattice side. Sometimes eq. (2.11) is also written with $p_{max}^2 / p^2(k)$ instead of $1 / p^2(k)$. However, $p_{max}^2 = 4d$ is a constant and can therefore be absorbed into the tuning parameter α .

Clearly, using eqs. (2.10), (2.12) and (2.13), we have

$$(\nabla \cdot A^{(g)})(x) = \frac{1}{2} \sum_{\mu=1}^d U_\mu^{(g)}(x) - U_\mu^{(g)\dagger}(x) - U_\mu^{(g)}(x - e_\mu) + U_\mu^{(g)\dagger}(x - e_\mu) \quad (2.15)$$

$$= \frac{1}{2} \left[\mathbf{w}(x) - \mathbf{w}^\dagger(x) \right] . \quad (2.16)$$

For a matrix $g \in SU(2)$ we use the parametrization

$$g \equiv g_0 \mathbb{1} + i \vec{\sigma} \cdot \vec{g} = \begin{pmatrix} g_0 + i g_3 & g_2 + i g_1 \\ -g_2 + i g_1 & g_0 - i g_3 \end{pmatrix} , \quad (2.17)$$

where the components of $\vec{\sigma} \equiv (\sigma^1, \sigma^2, \sigma^3)$ are the three Pauli matrices. Since $\mathbf{w}(x)$ is proportional to an $SU(2)$ matrix we can write $\mathbf{w}(x) = w_0(x) \mathbb{1} + i \vec{\sigma} \cdot \vec{w}(x)$ and

$$(\nabla \cdot A^{(g)})(x) = i \vec{\sigma} \cdot \vec{w}(x) . \quad (2.18)$$

Defining now

$$\vec{u}(x) \equiv \left\{ \hat{F}^{-1} \left[\frac{1}{p^2(k)} \hat{F} \vec{w} \right] \right\}(x) , \quad (2.19)$$

we have

$$g^{(Fourier)}(x) \propto \{ \mathbb{1} - i \alpha \vec{\sigma} \cdot \vec{u}(x) \} g(x) \quad (2.20)$$

and the Fourier acceleration update can be written as

$$g^{(Fourier)}(x) \equiv \frac{\mathbb{1} - i \alpha \vec{\sigma} \cdot \vec{u}(x)}{\sqrt{1 + \alpha^2 |\vec{u}(x)|^2}} g(x) . \quad (2.21)$$

In order to simplify the expression for $\vec{u}(x)$ in eq. (2.19), recall that (minus) the lattice Laplacian Δ [defined in eq. (3.7) below] is diagonal in momentum space, with elements given by $p^2(k)$. Therefore we have

$$\hat{F}^{-1} \frac{1}{p^2(k)} \hat{F} = (-\Delta)^{-1} \quad (2.22)$$

and

$$\vec{u}(x) = [(-\Delta)^{-1} \vec{w}](x) . \quad (2.23)$$

Clearly, the inverse of the (minus) Laplacian is defined only in the sub-space orthogonal to the constant mode $k = 0$. From the previous equation it is evident that the Fourier acceleration method is actually a Laplacian preconditioning algorithm.

3 The Case $\beta = \infty$

As said in the Introduction, we consider here the case in which all the link variables $U_\mu(x)$ are set equal to the identity matrix. Then, the minimizing functional (1.2) becomes

$$\begin{aligned} \mathcal{E}_U[g] &= 1 - \frac{1}{dV} \sum_{\mu=1}^d \sum_x \frac{\text{Tr}}{2} [g(x) g^\dagger(x + e_\mu)] \\ &= \frac{1}{V} \sum_x \frac{\text{Tr}}{2} \frac{1}{2d} \sum_{\mu=1}^d \{ [g(x) - g(x + e_\mu)] [g(x) - g(x + e_\mu)]^\dagger \} \end{aligned} \quad (3.1)$$

$$= \frac{1}{V} \sum_x \frac{1}{2d} \sum_{\mu=1}^d \| \mathbf{g}(x) - \mathbf{g}(x + e_\mu) \|^2 . \quad (3.2)$$

Here we have used $\text{Tr } g = \text{Tr } g^\dagger$, $g g^\dagger = \mathbb{1}$ and [using eq. (2.17)]

$$\frac{1}{2} \text{Tr} (g g^\dagger) = g_0 g_0 + \vec{g} \cdot \vec{g} \equiv \mathbf{g} \cdot \mathbf{g} = \|\mathbf{g}\|^2 , \quad (3.3)$$

where $\mathbf{g} \equiv (g_0, \vec{g})$ is a four-dimensional unit vector.

Equation (3.2) is very similar to the action of a four-vector massless free field $\mathbf{g}(x)$. The only difference is that our field must satisfy the constraint $\|\mathbf{g}(x)\|^2 = 1$, namely we are dealing with an $O(4)$ nonlinear σ -model. However, after a few sweeps, we expect the (gauge-transformed) gauge configuration $U_\mu^{(g)}(x) = g(x) g^\dagger(x + e_\mu)$ to be very close to the vacuum configuration, i.e. we expect the matrices $g(x)$ to be very close to a constant matrix. Since the minimizing

functional (1.3) is invariant under global gauge transformations, i.e. transformations in which $g(x)$ is x -independent, we can set this constant matrix equal to the identity matrix $\mathbb{1}$. Therefore, in the limit of large number of gauge-fixing sweeps t we can write⁵

$$g(x) = \mathbb{1} + i\epsilon \vec{\sigma} \cdot \vec{f}(x) + \mathcal{O}(\epsilon^2), \quad (3.4)$$

with $\epsilon \ll 1$. This approximation is justified because it is exactly in the limit of large t — in which only the slowest mode survives — that we evaluate the relaxation time of each algorithm.

Now, by using eq. (3.4), we can rewrite the minimizing functional (3.2) as

$$\mathcal{E}[f] = \frac{1}{V} \sum_x \frac{\epsilon^2}{2d} \sum_{\mu=1}^d \left| \vec{f}(x) - \vec{f}(x + e_\mu) \right|^2 + \mathcal{O}(\epsilon^3) \quad (3.5)$$

and, using the periodicity of the lattice,

$$\mathcal{E}[f] = \frac{1}{V} \frac{\epsilon^2}{2d} \sum_x \vec{f}(x) \cdot (-\Delta \vec{f})(x) + \mathcal{O}(\epsilon^3), \quad (3.6)$$

where $-\Delta$ is (minus) the lattice Laplacian, defined by

$$(-\Delta \vec{f})(x) \equiv \sum_{\mu=1}^d \left[2\vec{f}(x) - \vec{f}(x + e_\mu) - \vec{f}(x - e_\mu) \right]. \quad (3.7)$$

Therefore, by consistently keeping only terms up to order ϵ in $g(x)$, we have that $\mathcal{E}[f]$ — at the lowest order in ϵ — is the action of the three-vector massless free field $\vec{f}(x)$. In particular, we can update this field, in order to minimize the action, without taking into account the problem of the unitarity of g . In fact, from eq. (3.4) we have $g(x)g^\dagger(x) = \mathbb{1} + \mathcal{O}(\epsilon^2)$ for *any* field $\vec{f}(x)$.

It is not difficult to translate the update of the $g(x)$ variables for the five algorithms considered here into an update for the $\vec{f}(x)$ field. To this end, we use the approximation in eq. (3.4) and obtain [see eqs. (2.5) and (2.8)]

$$\begin{aligned} h(x) &= \sum_{\mu=1}^d \left[g^\dagger(x + e_\mu) + g^\dagger(x - e_\mu) \right] \\ &= 2d\mathbb{1} - i\epsilon \vec{\sigma} \cdot \sum_{\mu=1}^d \left[\vec{f}(x + e_\mu) + \vec{f}(x - e_\mu) \right] + \mathcal{O}(\epsilon^2) \end{aligned} \quad (3.8)$$

$$\begin{aligned} w(x) &= g(x) h(x) \\ &= 2d\mathbb{1} + i\epsilon \vec{\sigma} \cdot \sum_{\mu=1}^d \left[2\vec{f}(x) - \vec{f}(x + e_\mu) - \vec{f}(x - e_\mu) \right] + \mathcal{O}(\epsilon^2) \end{aligned} \quad (3.9)$$

and

$$\vec{w}(x) = \epsilon (-\Delta \vec{f})(x) + \mathcal{O}(\epsilon^2), \quad (3.10)$$

⁵ Note that with the parametrization $g(x) = g_0(x)\mathbb{1} + i\epsilon \vec{f}(x) \cdot \vec{\sigma} + \mathcal{O}(\epsilon^2)$ the unitarity condition for $g(x)$ implies that the corrections to $g_0(x) \approx 1$ start at order ϵ^2 .

where we used eq. (3.7). From these expressions it follows that [see eqs. (2.7), (2.9) and (2.23)]

$$\mathcal{N}(x) = 2d + \mathcal{O}(\epsilon^2), \quad (3.11)$$

$$\mathcal{T}(x) = 2 + \mathcal{O}(\epsilon^2), \quad (3.12)$$

$$\vec{u}(x) = \epsilon \vec{f}(x) + \mathcal{O}(\epsilon^2). \quad (3.13)$$

Actually, to be precise [see comment after eq. (2.23)], we should write eq. (3.13) as

$$\vec{u}(x) = \epsilon [\vec{f}(x) - \vec{f}_0] + \mathcal{O}(\epsilon^2), \quad (3.14)$$

where

$$\vec{f}_0 \equiv \frac{1}{V} \sum_x \vec{f}(x). \quad (3.15)$$

However, the zero mode of $g(x)$, and therefore of $\vec{f}(x)$, does not contribute to the value of the minimizing functional (3.1). Thus, in eq. (3.4), we can always consider a field $\vec{f}(x)$ with zero constant mode $\vec{f}_0$.

Now, by substituting eq. (3.4) and eqs. (3.8)–(3.13) into eqs. (2.1)–(2.4) and (2.21) we obtain for the updated $\vec{f}(x)$ variables (at the lowest order in ϵ)

$$\vec{f}^{(LosAl.)}(x) = \frac{1}{2d} \sum_{\mu=1}^d [\vec{f}(x + e_\mu) + \vec{f}(x - e_\mu)] \quad (3.16)$$

$$\vec{f}^{(cornell)}(x) = 2d\alpha \vec{f}^{(LosAl.)}(x) + (1 - 2d\alpha) \vec{f}(x) \quad (3.17)$$

$$\vec{f}^{(over)}(x) = \omega \vec{f}^{(LosAl.)}(x) + (1 - \omega) \vec{f}(x) \quad (3.18)$$

$$\vec{f}^{(stoc)}(x) = \begin{cases} 2 \vec{f}^{(LosAl.)}(x) - \vec{f}(x) & \text{with probability } p \\ \vec{f}^{(LosAl.)}(x) & \text{with probability } 1 - p \end{cases} \quad (3.19)$$

$$\vec{f}^{(Fourier)}(x) = (1 - \alpha) \vec{f}(x). \quad (3.20)$$

The interpretation of these updates is clear if we consider the *local* minimization of $\mathcal{E}[f]$, i.e. we consider all $f(x)$'s fixed for $x \neq y$, and we make explicit the dependence of the minimizing functional (3.5) on the value of the field $\vec{f}$ at site y , namely (to order ϵ^2)

$$\mathcal{E}[f(y)] = \frac{\epsilon^2}{V} \vec{f}(y) \cdot [\vec{f}(y) - 2 \vec{f}^{(LosAl.)}(y)] + \text{constant terms}, \quad (3.21)$$

where we have used eq. (3.16). Since $\vec{f}^{(LosAl.)}(y)$ does not depend on $\vec{f}(y)$ we can complete the square and write

$$\mathcal{E}[f(y)] = \frac{\epsilon^2}{V} \left| \vec{f}(y) - \vec{f}^{(LosAl.)}(y) \right|^2 + \text{constant terms}. \quad (3.22)$$

Then it is clear that the Los Alamos update brings this local functional to its minimum, while the choice $\vec{f}(y) \rightarrow 2 \vec{f}^{(LosAl.)}(y) - \vec{f}(y)$ does not change the value of $\mathcal{E}[f]$. From formulae (3.16)–(3.20) it is also evident that:

- The Los Alamos method corresponds to the usual *Gauss-Seidel* method [13, 14].
- The Cornell method coincides with the overrelaxation method if we use the relation [see eqs. (3.11), (3.17) and (3.18)]

$$\omega = 2d\alpha = \alpha\mathcal{N}(x) + \mathcal{O}(\epsilon^2) . \quad (3.23)$$

This confirms the result found analytically and numerically in two dimensions at finite β (see Sections 5 and 7.3 in Ref. [4]).

- The overrelaxation method corresponds to the usual *successive overrelaxation* method [13, 14].
- Since the vacuum configuration $\{U_\mu(x) = \mathbb{1}\}$ corresponds to $\vec{f}(x) = 0$ for all x , it is clear that the Fourier method can minimize $\mathcal{E}[f]$ in only one step if we set $\alpha = 1$. Thus, in this case, critical slowing-down is completely eliminated. Note that the tuning condition, i.e. $\alpha = 1$, does not depend on the dimension d of the lattice.

Moreover, it is now possible to study analytically the critical slowing-down for the four local algorithms following the analyses in Refs. [8, 9] (see next section). As we will see, the results of this analytic approach confirm the dynamic critical exponents found numerically in two dimensions at finite β [4]. Also, these results are particularly interesting with respect to the problem of tuning the improved local algorithms (see Section 6.2).

Let us notice that for t going to infinity all components of $\vec{f}(x)$ must go to zero for the algorithm to converge. Therefore, if in some basis we can write

$$f_t = C f_{t-1} , \quad (3.24)$$

where C is the updating matrix, then we should have

$$\lim_{t \rightarrow \infty} \|f_t\| = \lim_{t \rightarrow \infty} \|C^t f_0\| = 0 , \quad (3.25)$$

for any reasonable definition of the norm $\|f\|$ and of the initial condition f_0 . From the definition of the norm of a matrix (see for example Section 1.5 in [14]) it follows that

$$\|C^t f_0\| \leq \|C^t\| \|f_0\| . \quad (3.26)$$

Thus, the limit in eq. (3.25) is verified if $\|C^t\|$ goes to zero when t goes to infinity, i.e. if the matrix C^t goes to 0 in the same limit. This happens if and only if (see theorem 1.4 in [14]) the *spectral radius* $\rho(C)$ of the matrix C is smaller than 1, where

$$\rho(C) \equiv \max_{\lambda \in \sigma(C)} |\lambda| \quad (3.27)$$

and $\sigma(C)$ is the set of all the eigenvalues of the matrix C . One can also prove (see theorem 1.6 in [14]) that

$$\rho(C) = \lim_{t \rightarrow \infty} \|C^t\|^{1/t} \quad (3.28)$$

for any matrix norm $\|\cdot\|$. It follows that the algorithm converges if all the eigenvalues of the updating matrix C are smaller than 1 (in absolute value), i.e. if $\rho(C) < 1$. From now on, we

consider only the case $\rho(C) < 1$. Then, we can define the relaxation time $\tau > 0$ through the relation

$$e^{-1/\tau} \equiv \rho(C) , \quad (3.29)$$

namely

$$\tau = \frac{-1}{\log \rho(C)} . \quad (3.30)$$

Clearly if $\rho(C)$ is very close to 1, i.e. if

$$\rho(C) \approx 1 - \delta \quad (3.31)$$

with $0 < \delta \ll 1$, we find

$$\tau \approx \frac{1}{\delta} \approx \frac{1}{1 - \rho(C)} . \quad (3.32)$$

One can also consider the inequality

$$1 - |\lambda| \leq |1 - \lambda| , \quad (3.33)$$

which becomes an equality if the eigenvalue λ is real and positive (since we are considering $|\lambda| < 1$). This implies

$$1 - \rho(C) = 1 - \max_{\lambda \in \sigma(C)} |\lambda| = \min_{\lambda \in \sigma(C)} (1 - |\lambda|) \leq \min_{\lambda \in \sigma(C)} |1 - \lambda| . \quad (3.34)$$

Thus, if $\rho(C)$ is very close to 1 we obtain

$$\tau \approx \frac{1}{1 - \rho(C)} \geq \frac{1}{\min_{\lambda \in \sigma(C)} |1 - \lambda|} . \quad (3.35)$$

Notice that eqs. (3.24), (3.26), (3.28) and (3.29) imply that, in the limit of large t ,

$$\|f\| \sim e^{-t/\tau} . \quad (3.36)$$

Thus, if we know the matrix C and we can find its eigenvalues λ , we can evaluate the relaxation time τ using eq. (3.30) [or the approximate expressions (3.32), (3.35)]. On the contrary, for a numerical determination of τ one should use eq. (3.36) (for some definition of the norm $\|f\|$).

4 Analysis of Critical Slowing-Down

In this Section we review the analyses of critical slowing-down done in Refs. [8, 9] and we apply them to the four local algorithms considered in this paper.⁶ The only difference with respect to those references is that, in our case, we minimize the free-field action (3.5) instead of thermalizing the configuration $\{\vec{f}(x)\}$. Thus, their analyses can be applied directly to our case by setting the Gaussian noise $\eta(x)$ to zero. We stress that the results presented in this section are a straightforward application of the analyses reported in Refs. [8, 9] and that most of

⁶ See also Ref. [15] for a careful analysis of CSD for the local hybrid Monte Carlo algorithm (which is equivalent to the stochastic overrelaxation method) applied to the free-field case using various updating schemes. Here we will consider only the so-called even/odd update.

these results, but not all of them, can be found there and in other articles. However, we believe that our presentation has some interesting insights, which can help the reader understand how local algorithms deal with the problem of critical slowing-down. Moreover, these results will be extensively used in Section 5, where we study generalizations of the overrelaxation algorithm and of the stochastic overrelaxation algorithm.

Let us start by considering the **overrelaxation update** [see eqs. (3.16) and (3.18)]

$$\vec{f}^{(over)}(x) = -(\omega - 1) \vec{f}(x) + \frac{\omega}{2d} \sum_{\mu=1}^d \left[\vec{f}(x + e_\mu) + \vec{f}(x - e_\mu) \right]. \quad (4.1)$$

One can check that the condition $(\omega - 1)^2 < 1$ is sufficient to prove that this update never increases the value of the massless-free-field action [see eq. (3.22)]. Therefore we should have⁷ $\omega \in (0, 2)$. However, only when $\omega \in (1, 2)$ does one obtain [4] that the overrelaxation method performs better than the Los Alamos method, which corresponds to the case $\omega = 1$. For the Cornell method, it follows from eq. (3.23) that one should have $\alpha \mathcal{N}(x) \in (1, 2)$, which gives $\alpha \in (1/2d, 1/d)$ for the case $\beta = \infty$.

Clearly, using eq. (4.1), we need to know the value of the field $\vec{f}$ only at the site x and at the nearest-neighbor sites $x \pm e_\mu$ in order to update $\vec{f}(x)$. Note that a site is defined to be even or odd according to whether the quantity

$$|x| \equiv \sum_{\mu=1}^d x_\mu \quad (4.2)$$

is even or odd. Thus, if we consider lattices with an even number of sites in each direction and a checkerboard ordering, then we can first update all the even sites and subsequently all the odd ones, and so on. In order to implement the checkerboard update we can rewrite the update (4.1) as

$$\begin{aligned} f_{t+1}^a(x) &= -(\omega - 1) f_t^a(x) \\ &+ \frac{\omega}{4d} \sum_{\mu=1}^d \left\{ \left[1 + (-1)^{|x|} \right] \left[f_t^a(x + e_\mu) + f_t^a(x - e_\mu) \right] \right. \\ &\quad \left. + \left[1 - (-1)^{|x|} \right] \left[f_{t+1}^a(x + e_\mu) + f_{t+1}^a(x - e_\mu) \right] \right\}, \end{aligned} \quad (4.3)$$

where $f^a(x)$ are the three “color” components of $\vec{f}(x)$ and t denotes the number of sweeps through the entire lattice. Notice that when we update the odd sites, i.e. when $(-1)^{|x|} = -1$, we use for the update the value of the newly updated field f_{t+1}^a at even sites.

The idea in Neuberger’s article [8] is to consider the Fourier transform

$$\tilde{f}^a(k) \equiv \sum_x f^a(x) \exp(-2\pi i k \cdot x) \quad (4.4)$$

of eq. (4.3). To this end one can use the relation

$$(-1)^{|x|} = \exp(-2\pi i T \cdot x), \quad (4.5)$$

⁷ As shown in Section 3.3 of Ref. [4], this result also applies to the update given in eq. (2.3) when considering the minimizing functional (1.2).

where the vector T has components given by

$$T_\mu = \frac{1}{2} \quad \mu = 1, \dots, d. \quad (4.6)$$

In this way one obtains

$$\begin{aligned} \tilde{f}_{t+1}^a(k) &= -(\omega - 1) \tilde{f}_t^a(k) \\ &+ \omega c(k) \left[\tilde{f}_t^a(k) + \tilde{f}_{t+1}^a(k) - \tilde{f}_t^a(k + T) + \tilde{f}_{t+1}^a(k + T) \right], \end{aligned} \quad (4.7)$$

where we defined

$$c(k) \equiv \frac{1}{2d} \sum_{\mu=1}^d \cos(2\pi k_\mu). \quad (4.8)$$

One can write eq. (4.7) also for $\tilde{f}_{t+1}^a(k + T)$, namely

$$\begin{aligned} \tilde{f}_{t+1}^a(k + T) &= -(\omega - 1) \tilde{f}_t^a(k + T) \\ &- \omega c(k) \left[\tilde{f}_t^a(k + T) + \tilde{f}_{t+1}^a(k + T) - \tilde{f}_t^a(k) + \tilde{f}_{t+1}^a(k) \right]. \end{aligned} \quad (4.9)$$

Then, equations (4.7) and (4.9) can be written as a system of two equations

$$A(k, \omega) \begin{pmatrix} \tilde{f}_{t+1}^a(k) \\ \tilde{f}_{t+1}^a(k + T) \end{pmatrix} = B(k, \omega) \begin{pmatrix} \tilde{f}_t^a(k) \\ \tilde{f}_t^a(k + T) \end{pmatrix}, \quad (4.10)$$

where the 2×2 matrices $A(k, \omega)$ and $B(k, \omega)$ are given by

$$A(k, \omega) \equiv \mathbb{1} + \omega c(k) \begin{pmatrix} -1 & -1 \\ 1 & 1 \end{pmatrix} \quad (4.11)$$

$$B(k, \omega) \equiv -(\omega - 1) \mathbb{1} + \omega c(k) \begin{pmatrix} 1 & -1 \\ 1 & -1 \end{pmatrix}. \quad (4.12)$$

Let us now define

$$C(k, \omega) \equiv A^{-1}(k, \omega) B(k, \omega); \quad (4.13)$$

then, the update of the field $\tilde{f}^a$, namely one even update followed by an odd update, can be written (in momentum space) as [see eq. (4.10)]

$$\begin{pmatrix} \tilde{f}_{t+1}^a(k) \\ \tilde{f}_{t+1}^a(k + T) \end{pmatrix} = C(k, \omega) \begin{pmatrix} \tilde{f}_t^a(k) \\ \tilde{f}_t^a(k + T) \end{pmatrix}. \quad (4.14)$$

Notice that the determinant of $A(k, \omega)$ is equal to 1 for any ω , i.e. this matrix can always be inverted:

$$A^{-1}(k, \omega) = \mathbb{1} + \omega c(k) \begin{pmatrix} 1 & 1 \\ -1 & -1 \end{pmatrix}. \quad (4.15)$$

This gives

$$C(k, \omega) = \left[2\omega^2 c^2(k) - (\omega - 1) \right] \mathbb{1} + \omega c(k) \begin{pmatrix} 2 - \omega & -\omega [1 + 2c(k)] \\ \omega [1 - 2c(k)] & -(2 - \omega) \end{pmatrix}. \quad (4.16)$$

It is easy to check that the eigenvalues of the matrix $C(k, \omega)$ are given by

$$\lambda_{\pm}(k, \omega) = \left[2\omega^2 c^2(k) - (\omega - 1) \right] \pm \sqrt{\left[2\omega^2 c^2(k) - (\omega - 1) \right]^2 - (\omega - 1)^2} \quad (4.17)$$

$$= \left[2\omega^2 c^2(k) - (\omega - 1) \right] \pm 2\omega \sqrt{\omega^2 c^4(k) - (\omega - 1) c^2(k)} . \quad (4.18)$$

Then, if we can prove that $|\lambda_{\pm}(k, \omega)| < 1$, we can use eq. (3.30) and write

$$\tau = \frac{-1}{\log(\max_{k \neq 0} |\lambda_{\pm}(k, \omega)|)} , \quad (4.19)$$

where we don't consider the constant (or zero) mode because it does not contribute to the action (3.5).

We can obtain the eigenvalues $\lambda_{\pm}(k, \omega)$ also working in a slightly different way, namely following now Ref. [9]. The main difference with respect to the approach used above (based on Ref. [8]) is that, instead of considering the Fourier transform of eq. (4.3), one applies to eq. (4.1) the Fourier-like transform

$$f^{a,\pm}(k) \equiv \sum_x f^a(x) \left[1 \pm e^{-2\pi i T \cdot x} \right] \exp(-2\pi i k \cdot x) , \quad (4.20)$$

with T defined in eqs. (4.5) and (4.6). By using the result $\exp(\pm 2\pi i T_{\mu}) = -1$ and the periodicity of the lattice one can verify that

$$\sum_x f^a(x + e_{\mu}) \left[1 \pm e^{-2\pi i T \cdot x} \right] \exp(-2\pi i k \cdot x) = e^{+2\pi i k_{\mu}} f^{a,\mp}(k) , \quad (4.21)$$

$$\sum_x f^a(x - e_{\mu}) \left[1 \pm e^{-2\pi i T \cdot x} \right] \exp(-2\pi i k \cdot x) = e^{-2\pi i k_{\mu}} f^{a,\mp}(k) . \quad (4.22)$$

Thus, using eq. (4.1) and eqs. (4.20)–(4.22) and by updating first the $f^{a,+}(k)$ components and then the $f^{a,-}(k)$ components, we obtain

$$\begin{pmatrix} f_{t+1}^{a,+}(k) \\ f_{t+1}^{a,-}(k) \end{pmatrix} = M(k, \omega) \begin{pmatrix} f_t^{a,+}(k) \\ f_t^{a,-}(k) \end{pmatrix} , \quad (4.23)$$

where

$$M(k, \omega) \equiv -(\omega - 1) \mathbb{1} + 2\omega c(k) \begin{pmatrix} 0 & 1 \\ -(\omega - 1) & 2\omega c(k) \end{pmatrix} . \quad (4.24)$$

It is straightforward to check that the matrix $M(k, \omega)$ also has eigenvalues $\lambda_{\pm}(k, \omega)$ [given in eqs. (4.17) and (4.18)], namely $M(k, \omega)$ is the matrix $C(k, \omega)$ [see eq. (4.16)] written in a different basis. Indeed, with

$$R \equiv \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix} , \quad (4.25)$$

we have

$$M(k, \omega) = R C(k, \omega) R^{-1} . \quad (4.26)$$

Note that we started the analysis of the overrelaxation update from one equation, namely eq. (4.1), and we are now considering a system of two equations. Thus, we should avoid double

counting for the momenta [9] and set, for example, $k_d N = 0, 1, \dots, N/2 - 1$ and $k_i N = 0, 1, \dots, N - 1$ for $i = 1, \dots, d - 1$. Therefore, in the limit of infinite lattice side N , the quantity $c(k)$ defined in eq. (4.8) takes values in the interval $(-1/2, 1/2]$ and the lattice momentum $p^2(k)$ [see eq. (2.14)] takes values in $[0, 4d)$. Also, since we know that CSD is due to the long-wavelength modes, which are usually the ones with slowest relaxation, we should consider $c(k)$ in the limit of small momenta. Obviously, if $k_\mu = 0$ for all μ then $c(k) = 1/2$ and, using the fact that $\omega \in (1, 2)$, one can check that $\lambda_+(0, \omega) = 1$ and $\lambda_-(0, \omega) = (1 - \omega)^2 < 1$, i.e. the constant (or zero) mode does not converge to zero. However, as said above, this mode does not contribute to the action (3.5) and it is therefore not relevant when studying CSD. On the contrary, for the smallest non-zero momentum — corresponding to $k_i = 0$ for $i = 1, \dots, d - 1$ and $k_d = 1/N$ — we have

$$c_{sm}(N) = \frac{1}{2d} \left[d - 1 + \cos \left(\frac{2\pi}{N} \right) \right] \quad (4.27)$$

and, in the limit of large lattice side N ,

$$c_{sm}(N) \approx \frac{1}{2} \left[1 - \frac{2\pi^2}{dN^2} \right] \equiv \frac{1}{2} [1 - \zeta(N)] , \quad (4.28)$$

namely we get the largest value of $c(k)$ smaller than $1/2$. This case is important because, as we will see below, the largest eigenvalue of the matrix $C(k, \omega)$ is very close to 1 exactly for the smallest non-zero momentum in the limit of large N . Thus, the quantity $\zeta(N)$ will play a central role in the study of CSD for the four local algorithms considered here.

Note that eqs. (4.27) and (4.28) are valid also in the case of asymmetric lattices if we set $N = \max_\mu N_\mu$. It is also interesting to check that $c(k)$ switches sign when k_μ goes to $k_\mu + T_\mu$ for all μ [see eq. (4.8)]. Thus, we have $|c(k)| \approx 1/2$ not only for small momenta $p^2(k) \approx 0$ but also for the largest momenta $p^2(k) \approx 4d$, corresponding to small-wavelength modes. This is obvious if we observe that

$$c(k) \equiv \frac{1}{2} \left[\frac{1}{d} \sum_{\mu=1}^d \cos(2\pi k_\mu) \right] = \frac{1}{2} \left[1 - \frac{2}{d} \sum_{\mu=1}^d \sin^2(\pi k_\mu) \right] = \frac{1}{2} \left[1 - \frac{p^2(k)}{2d} \right] , \quad (4.29)$$

where we used eq. (2.14). Indeed, if we consider the largest momentum $p^2(k)$, namely if we set $k_i = 1/2$ for $i = 1, \dots, d - 1$ and $k_d = 1/2 - 1/N$, then we obtain

$$c_{lm}(N) = \frac{1}{2d} \left[-d + 1 + \cos \left(\pi - \frac{2\pi}{N} \right) \right] = \frac{1}{2d} \left[-d + 1 - \cos \left(\frac{2\pi}{N} \right) \right] = -c_{sm}(N) . \quad (4.30)$$

Therefore, in the limit of large lattice side N , the largest value of $|c(k)|$ smaller than $1/2$ is given by

$$|c(k(N))| = \frac{1}{2} |1 - \zeta(N)| , \quad (4.31)$$

corresponding both to the smallest non-zero momentum and to the largest momentum. Since the eigenvalues $\lambda_\pm(k, \omega)$ are functions only of $c^2(k)$ — or equivalently of $|c(k)|$ — and since they do not depend on the sign of the quantity $c(k)$ [see eqs. (4.17) and (4.18)], the previous result implies that these large momenta contribute to CSD too. This unexpected effect is due to the even/odd update which couples the low- and high-frequency modes [15].

4.1 Los Alamos Method

As said before, the Los Alamos update is obtained from eq. (4.1) by setting $\omega = 1$. Then, the eigenvalues $\lambda_{\pm}(k, \omega)$ of the matrix $C(k, \omega)$ become [see eqs. (4.8) and (4.17)]

$$\lambda_{-}(k, 1) = 0 \quad (4.32)$$

$$\lambda(k) \equiv \lambda_{+}(k, 1) = 4c^2(k) = \left[\frac{1}{d} \sum_{\mu=1}^d \cos(2\pi k_{\mu}) \right]^2, \quad (4.33)$$

and, in the limit of infinite lattice side N , we can consider k_d taking values in the interval $[0, 1/2]$ and k_i in the interval $[0, 1)$ for $i = 1, \dots, d-1$ [see comment after eq. (4.26)]. It is obvious that, if $k_{\mu} = 0$ for all μ , then $\lambda(k)$ is equal to 1, while in any other case it is strictly smaller than 1. Thus, all the Fourier modes relax, except for the constant (or zero) mode which, however, does not contribute to the action (3.5). Moreover, $\lambda(k)$ is always nonnegative. Therefore we can write

$$0 \leq |\lambda(k)| = \lambda(k) \leq 1. \quad (4.34)$$

It follows that [see eq. (4.19)] the relaxation time of the Los Alamos method is given by

$$\tau = \frac{-1}{\log(\max_{k \neq 0} \lambda(k))} \quad (4.35)$$

and if $\lambda(k)$ is very close to 1 — i.e. if $|c(k)| \approx 1/2$ — we have [see eq. (3.32)]

$$\tau \approx \frac{1}{1 - \max_{k \neq 0} \lambda(k)}. \quad (4.36)$$

From the previous section we know that this is the case when one considers the smallest non-zero momentum — or the largest momentum — in the limit of large lattice side N . Then, using eq. (4.31) we obtain

$$\max_{k \neq 0} \lambda(k) = [1 - \zeta(N)]^2 \approx 1 - 2\zeta(N), \quad (4.37)$$

from which follows

$$\tau_{LosAlamos} \approx \frac{1}{2\zeta(N)} = \frac{d}{4\pi^2} N^2. \quad (4.38)$$

So, as expected, the dynamic critical exponent z is equal to 2.

4.2 Overrelaxation Method⁸

As seen above, the update for the overrelaxation algorithm is given by eq. (4.1) with the parameter ω taking values in the interval $(1, 2)$ and its relaxation time is related to the eigenvalues $\lambda_{\pm}(k, \omega)$ of the matrix $C(k, \omega)$ [see eqs. (4.17) and (4.18)] through the relation [see eq. (4.19)]

$$\tau = \frac{-1}{\log(\max_{k \neq 0} |\lambda_{\pm}(k)|)}, \quad (4.39)$$

⁸ The results presented in this section apply also to the Cornell method [see eqs. (3.17), (3.18) and (3.23)].

provided that $\max_{k \neq 0} |\lambda_{\pm}(k)| < 1$. As said at the end of Section 3, we must verify that this condition is satisfied to ensure the convergence of the algorithm. To this end, following Ref. [8], we define

$$r(k, \omega) \equiv 1 - \frac{2\omega^2 c^2(k)}{\omega - 1} \quad (4.40)$$

and, using the fact that $\omega \in (1, 2)$, we can write eq. (4.17) as

$$\lambda_{\pm}(k, \omega) = (\omega - 1) \left[-r(k, \omega) \pm \sqrt{r^2(k, \omega) - 1} \right]. \quad (4.41)$$

Note that $r(k, \omega) \in (-\infty, 1]$. There are therefore two possibilities, described below.

- 1) $r(k, \omega) \in [-1, 1]$ for all values of k , namely we have to impose the condition $r(k, \omega) \geq -1$ for all k . In this case the eigenvalues $\lambda_{\pm}(k, \omega)$ are complex conjugates of each other and we have

$$|\lambda_{\pm}(k, \omega)| = |\omega - 1|, \quad (4.42)$$

namely $|\lambda_{\pm, \omega}(k)|$ is independent of k (see Refs. [2, 8, 9]). Also note that

$$|\omega - 1| = \omega - 1 < 1. \quad (4.43)$$

- 2) $r(\bar{k}, \omega) < -1$ for some values of k , denoted as $\bar{k}$. In this case the corresponding eigenvalues $\lambda_{\pm}(\bar{k}, \omega)$ are real and we can verify that $0 < \lambda_{-}(\bar{k}, \omega) < \lambda_{+}(\bar{k}, \omega)$. From eq. (4.40) it is clear that we can obtain $r(k, \omega) < -1$ only for the largest values of $c^2(k)$, i.e. $c^2(k) \approx 1/4$, corresponding to momenta $p^2(k) \approx 0$ or to momenta $p^2(k) \approx 4d$ (see comment at the end of Section 4). Considering now eq. (4.40) with $r(\bar{k}, \omega) < -1$ we get

$$0 < \omega - 1 < \omega^2 c^2(\bar{k}) \quad (4.44)$$

and

$$\omega^2 c^2(\bar{k}) < 2\omega^2 c^2(\bar{k}) - (\omega - 1). \quad (4.45)$$

Also, since $c(k) \in (-1/2, 1/2]$ for all values of k , we have

$$c^2(k) \leq \frac{1}{4} \quad (4.46)$$

and one can check that

$$0 < 2\omega^2 c^2(\bar{k}) - (\omega - 1) \leq \frac{1}{2}(\omega - 1)^2 + \frac{1}{2} \quad (4.47)$$

and

$$\omega^2 c^2(\bar{k}) - (\omega - 1) \leq \frac{(2 - \omega)^2}{4}. \quad (4.48)$$

These inequalities imply [see eq. (4.18)]

$$\lambda_{+}(\bar{k}, \omega) \leq \frac{1}{2}(\omega - 1)^2 + \frac{1}{2} + \omega \frac{2 - \omega}{2} \leq 1; \quad (4.49)$$

moreover, $\lambda_{+}(\bar{k}, \omega)$ is equal to 1 only if $c^2(\bar{k}) = 1/4$, i.e. if $\bar{k} = 0$. Finally, from eqs. (4.17), (4.44) and (4.45) one can prove that $\lambda_{+}(\bar{k}, \omega) > \omega - 1$.

To sum up we can say that, with $\omega \in (1, 2)$, there are two different situations. If the inequality $r(k, \omega) \geq -1$ is satisfied for all values of k , then the eigenvalues $\lambda_{\pm}(k, \omega)$ are complex conjugates of each other with absolute value independent of k and given by $\omega - 1$. In this case we have that the largest eigenvalue is close to 1 — which is the interesting case when one studies CSD — only when ω is close to 2. If, on the contrary, we have that $r(\bar{k}, \omega) < -1$ for some values $\bar{k}$, then the largest eigenvalue of the matrix $C(k, \omega)$ is real and given by $\max_{\bar{k} \neq 0} \lambda_+(\bar{k}, \omega)$. (Note that $\max_{\bar{k} \neq 0}$ is taken only over the values $\bar{k}$.) In this case it is easy to check that, in the limit of large N ,

$$\max_{\bar{k} \neq 0} \lambda_+(\bar{k}, \omega) \approx 1 - \frac{2\omega \zeta(N)}{2 - \omega} = 1 - \frac{4\omega \pi^2}{(2 - \omega) d N^2}, \quad (4.50)$$

where we used eqs. (4.17) and (4.31).

In order to study CSD for the overrelaxation algorithm one usually writes

$$\omega = \frac{2}{1 + \Omega} \quad (4.51)$$

with $\Omega \in (0, 1)$. By using eq. (4.51) we can then rewrite $r(k, \omega)$ as

$$r(k, \Omega) \equiv 1 - \frac{8c^2(k)}{1 - \Omega^2}. \quad (4.52)$$

We now discuss separately the two cases considered above.

Case 1), i.e. if $r(k, \omega) \geq -1$ for all values of k , corresponds to

$$\Omega^2 \leq 1 - 4c^2(k). \quad (4.53)$$

Since this condition should be satisfied for all values of k we must have

$$\Omega^2 \leq 1 - 4 \max_{k \neq 0} c^2(k), \quad (4.54)$$

where again we don't consider the zero mode $k = 0$. When N goes to infinity we find [using eq. (4.31)]

$$\Omega^2 \leq 2\zeta(N) = \frac{4\pi^2}{d N^2}, \quad (4.55)$$

namely Ω goes to zero. In this case we have

$$|\lambda_{\pm}(k, \omega)| = \omega - 1 = \frac{1 - \Omega}{1 + \Omega}. \quad (4.56)$$

In the limit of small Ω we obtain

$$|\lambda_{\pm}(k, \omega)| \approx 1 - 2\Omega \quad (4.57)$$

and the relaxation time becomes [see eq. (3.32)]

$$\tau \approx \frac{1}{1 - \max_{k \neq 0} |\lambda_{\pm}(k, \omega)|} \approx \frac{1}{2\Omega}. \quad (4.58)$$

So, if we want to minimize the relaxation time τ we have to maximize the value of Ω allowed by the inequality (4.55), i.e we have to set

$$\Omega = \frac{2\pi}{\sqrt{d}N}. \quad (4.59)$$

In this way we get

$$\tau_{over} \approx \frac{\sqrt{d}}{4\pi} N \quad (4.60)$$

and, as expected, we have $z = 1$. Note that the tuning for Ω given by eq. (4.59) implies

$$\omega = \frac{2}{1 + \Omega} = 2 \left(1 + \frac{2\pi}{\sqrt{d}N} \right)^{-1}. \quad (4.61)$$

Case 2) corresponds to the existence of values $\bar{k}$ satisfying the inequality

$$\Omega^2 > 1 - 4c^2(\bar{k}). \quad (4.62)$$

In this case, as we saw above, we have

$$\max_{\bar{k} \neq 0} \lambda_+(\bar{k}, \omega) \approx 1 - \frac{4\omega\pi^2}{(2 - \omega)dN^2}. \quad (4.63)$$

This implies

$$\tau \approx \frac{1}{1 - \max_{\bar{k} \neq 0} \lambda_+(\bar{k}, \omega)} \approx \frac{(2 - \omega)dN^2}{4\omega\pi^2} \quad (4.64)$$

and in order to minimize the relaxation time τ we have to minimize $(2 - \omega)/\omega = \Omega$. This can be done by choosing $\Omega \sim 1/N^m$, yielding τ proportional to N^{2-m} and $z = 2 - m$. In particular, it might seem possible to set $m = 2$ so that τ becomes constant in N and CSD is completely eliminated. However, we note that the tuning of Ω must be done while still satisfying eq. (4.62), since it defines what we are calling “case 2)”. This implies the condition

$$\frac{1}{N^{2m}} \sim \Omega^2 > 1 - 4c^2(\bar{k}) \sim \frac{1}{N^2}, \quad (4.65)$$

namely $m \leq 1$ and $z \geq 1$. Thus, since we want to minimize Ω , we have to set $m = 1$ and impose that the inequality (4.62) become the equality

$$\Omega^2 = 1 - 4 \max_{k \neq 0} c^2(k). \quad (4.66)$$

We can conclude by saying that — in both cases considered above — the **best** tuning for the overrelaxation algorithm is obtained from the condition (4.66). Then, the largest eigenvalues $\lambda_{\pm}(k, \omega)$ of the matrix $C(k, \omega)$ with $k \neq 0$ are real and both equal to $\omega - 1$ [corresponding to $r(k, \Omega) = -1$], while for all the other non-zero momenta these eigenvalues are complex conjugates of each other [corresponding to $r(k, \Omega) > -1$].

If we do **not** tune the value of the parameter Ω (or equivalently of the parameter ω), we can consider two limiting cases. When Ω is so small that the condition

$$\Omega^2 < 2\zeta(N) \quad (4.67)$$

is satisfied for all the lattice sides N considered, then $r(k, \omega) > -1$ for all momenta and we obtain [see eq. (4.58)]

$$\tau \approx \frac{1}{2\Omega} . \quad (4.68)$$

Thus, the relaxation time τ is constant in N and we get $z = 0$. However, τ is very large, and even though the number of gauge-fixing sweeps n_{gf} is in this case independent of the lattice side N , we need a very large n_{gf} in order to complete the gauge fixing even for relatively small lattice volumes. On the contrary if Ω is large and, for all lattice sides N considered, we can find non-zero momenta $p^2(\bar{k})$ such that the condition

$$\Omega^2 > 1 - 4c^2(\bar{k}) \quad (4.69)$$

is satisfied, namely $r(\bar{k}, \omega) < -1$, then the relaxation time τ is given by [see eq. (4.64)]

$$\tau \approx \frac{(2 - \omega) d N^2}{4 \omega \pi^2} \quad (4.70)$$

and $z = 2$. Nevertheless, in this case, the overrelaxation algorithm works better than the Los Alamos method: in fact, using eq. (4.38), we obtain

$$\tau \approx \frac{2 - \omega}{\omega} \tau_{LosAlamos} = \Omega \tau_{LosAlamos} \quad (4.71)$$

and τ is always smaller [for $\omega \in (1, 2)$, i.e. $\Omega \in (0, 1)$] than the Los Alamos relaxation time. Clearly, when N goes to infinity with Ω fixed, we always obtain eq. (4.70) and find $z = 2$.

As a final remark, we note that this analysis implies that the dynamic critical exponent z of the overrelaxation algorithm depends only on the relation between Ω^2 and $2\zeta(N)$, namely if for all values of N considered we set Ω^2 much smaller than, equal to, or much larger than $2\zeta(N)$ we have that the dynamic critical exponent z is equal to 0, 1 or 2 respectively.

4.3 Stochastic Overrelaxation Method

In this section we want to analyze the critical slowing-down of the stochastic overrelaxation method. As explained in Ref. [4], this algorithm is similar in spirit to the idea behind the so-called *hybrid* version of overrelaxed algorithms (HOR), which are used to speed up Monte Carlo simulations of spin models, lattice gauge theory, etc. [2, 9, 16]. In these algorithms, m micro-canonical (or energy conserving) update sweeps are done followed by one standard local ergodic update (such as Metropolis or heat-bath) sweep over the lattice. Actually, for the Gaussian model, it has been proven [9] that the best result is obtained when the micro-canonical steps are chosen at random, namely when m is the average number of micro-canonical sweeps between two subsequent ergodic updates. This is essentially what is done in the stochastic overrelaxation method [see eq. (2.4)], with $m/(m+1)$ equal in average to p or, equivalently, m equal on average to $p/(1-p)$.

In order to follow the analysis in Ref. [9], we suppose that the stochastic overrelaxation method is implemented as an HOR algorithm: m sweeps using the “micro-canonical” update [see eq. (4.1) with $\omega = 2$]

$$\vec{f}(x) = -\vec{f}(x) + \frac{1}{d} \sum_{\mu=1}^d \left[\vec{f}(x + e_{\mu}) + \vec{f}(x - e_{\mu}) \right] , \quad (4.72)$$

which does not change the value of the minimizing functional, and one sweep using the Los Alamos update [see eq. (4.1) with $\omega = 1$]

$$\vec{f}(x) = \frac{1}{2d} \sum_{\mu=1}^d \left[\vec{f}(x + e_{\mu}) + \vec{f}(x - e_{\mu}) \right], \quad (4.73)$$

which brings the minimizing functional to its local absolute minimum. Let us notice that, for $\omega = 2$, the eigenvalues $\lambda_{\pm}(k, \omega)$ in eq. (4.18) become

$$\lambda_{\pm}(k, 2) = \left[-1 + 8c^2(k) \right] \pm i4\sqrt{c^2(k) - 4c^4(k)} = \exp[\pm i\theta(k)], \quad (4.74)$$

where we define $\theta(k)$ such that

$$\cos[\theta(k)/2] \equiv 2c(k). \quad (4.75)$$

Clearly, in this case, we have $|\lambda_{\pm}(k, 2)| = 1$ for all values of k and, as expected, none of the Fourier modes relaxes.

If we consider as *one sweep* of the lattice the combination of m sweeps using the update (4.72) and one sweep using the update (4.73), then the matrix that defines this combined update (in momentum space) is given by

$$\tilde{C}(k, m) = C(k, 1) [C(k, 2)]^m, \quad (4.76)$$

where $C(k, \omega)$ is defined in eq. (4.16), or by

$$\tilde{M}(k, m) = M(k, 1) [M(k, 2)]^m, \quad (4.77)$$

with $M(k, \omega)$ defined in eq. (4.24). Since it is easier to work with $M(k, \omega)$ than with $C(k, \omega)$ we will use eq. (4.77). However, one can check that $\tilde{C}(k, m)$ and $\tilde{M}(k, m)$ have the same eigenvalues⁹. Then, following Ref. [9], we can write

$$M(k, 2) = \begin{pmatrix} -1 & 4c(k) \\ -4c(k) & -1 + 16c^2(k) \end{pmatrix} \quad (4.78)$$

$$= V(k) \begin{pmatrix} \exp[-i\theta(k)] & 0 \\ 0 & \exp[i\theta(k)] \end{pmatrix} V^{-1}(k), \quad (4.79)$$

where $\theta(k)$ is defined in eq. (4.75) and the matrix $V(k)$ is given by

$$V(k) \equiv \begin{pmatrix} \exp[i\theta(k)/2] & \exp[-i\theta(k)/2] \\ 1 & 1 \end{pmatrix}. \quad (4.80)$$

This implies that

$$[M(k, 2)]^m = V(k) \begin{pmatrix} \exp[-im\theta(k)] & 0 \\ 0 & \exp[im\theta(k)] \end{pmatrix}^m V^{-1}(k) \quad (4.81)$$

$$= V(k) \begin{pmatrix} \exp[-im\theta(k)] & 0 \\ 0 & \exp[im\theta(k)] \end{pmatrix} V^{-1}(k). \quad (4.82)$$

⁹ This is immediate if we consider that the matrix R defined in eq. (4.25) is independent of k and ω . Therefore the relation (4.26) between the matrices $M(k, \omega)$ and $C(k, \omega)$ is also valid for the matrices $\tilde{M}(k, m)$ and $\tilde{C}(k, m)$.

One can also write the matrix $M(k, 1)$ in the dyadic form

$$M(k, 1) = 2c(k) \begin{pmatrix} 0 & 1 \\ 0 & 2c(k) \end{pmatrix} = 2c(k) \begin{pmatrix} 1 \\ 2c(k) \end{pmatrix} \cdot (0, 1) \quad (4.83)$$

and, using eqs. (4.77), (4.82) and (4.83) we obtain

$$\widetilde{M}(k, m) = \frac{2c(k)}{\sin[\theta(k)/2]} \begin{pmatrix} 1 \\ 2c(k) \end{pmatrix} \cdot \left(-\sin[m\theta(k)], \sin\left[\left(m + \frac{1}{2}\right)\theta(k)\right] \right). \quad (4.84)$$

The eigenvalues of this matrix are equal to zero and to

$$\cos\left[\frac{\theta(k)}{2}\right] \cos\left[\left(m + \frac{1}{2}\right)\theta(k)\right]. \quad (4.85)$$

However, m is not fixed but varies between zero and infinity with probability $p^m(1-p)$. This gives an average value

$$\langle m \rangle \equiv \sum_{m=0}^{\infty} m p^m (1-p) = \frac{\sum_{m=0}^{\infty} m p^m}{\sum_{m=0}^{\infty} p^m} = p \frac{d}{dp} \log \sum_{m=0}^{\infty} p^m = \frac{p}{1-p}, \quad (4.86)$$

as said above. Thus, instead of looking for the eigenvalues of the matrix $\widetilde{M}(k, m)$ we should consider the matrix

$$\mathcal{M}(k, p) \equiv (1-p) \sum_{m=0}^{\infty} p^m \widetilde{M}(k, m). \quad (4.87)$$

After writing eq. (4.84) as

$$\begin{aligned} \widetilde{M}(k, m) &= \frac{2c(k)}{\sin[\theta(k)/2]} \\ &\times \begin{pmatrix} 1 \\ 2c(k) \end{pmatrix} \cdot \left[\text{Im} \left(-\exp[i m \theta(k)], \exp\left[i \left(m + \frac{1}{2}\right) \theta(k)\right] \right) \right], \end{aligned} \quad (4.88)$$

it is straightforward to check that the matrix $\mathcal{M}(k, p)$ can be written in the dyadic form

$$\begin{aligned} \mathcal{M}(k, p) &= \frac{(1-p) \cos[\theta(k)/2]}{[1 + p^2 - 2p \cos \theta(k)] \sin[\theta(k)/2]} \\ &\times \begin{pmatrix} 1 \\ \cos[\theta(k)/2] \end{pmatrix} \cdot (-p \sin \theta(k), (1+p) \sin[\theta(k)/2]) \end{aligned} \quad (4.89)$$

and has eigenvalues zero and

$$\lambda(k, p) = \frac{(1-p)^2 \cos^2[\theta(k)/2]}{(1-p)^2 + 4p \sin^2[\theta(k)/2]}. \quad (4.90)$$

Clearly this eigenvalue is nonnegative for any $p \in (0, 1)$ and for $p = 0$ (i.e. $\langle m \rangle = 0$) we obtain the non-zero eigenvalue $\lambda(k, 0) = \cos^2[\theta(k)/2] = 4c^2(k)$ of the Los Alamos method [see eq. (4.33)].

Note that, since the matrix $\mathcal{M}(k, p)$ describes (on average) $\langle m \rangle + 1$ sweeps of the lattice, eq. (3.29) is not correct for the stochastic overrelaxation algorithm. In fact, in this case, the relaxation time τ is related to the eigenvalue $\lambda(k, p)$ by the expression [9]

$$\max_{k \neq 0} |\lambda(k, p)| = \max_{k \neq 0} \lambda(k, p) \equiv e^{-\langle m \rangle + 1 / \tau}, \quad (4.91)$$

namely

$$\frac{\tau}{\langle m \rangle + 1} = \frac{-1}{\log(\max_{k \neq 0} \lambda(k, p))}. \quad (4.92)$$

In order to study CSD for the stochastic overrelaxation algorithm, we introduce $P \in (0, 1)$ and write

$$p = \frac{1 - P}{1 + P}. \quad (4.93)$$

Then, the eigenvalue in eq. (4.90) becomes

$$\lambda(k, P) = \frac{P^2 \cos^2[\theta(k)/2]}{1 + (P^2 - 1) \cos^2[\theta(k)/2]}. \quad (4.94)$$

Also, using eqs. (4.29) and (4.75), one obtains

$$\cos[\theta(k)/2] = 2c(k) = 1 - \frac{p^2(k)}{2d} \equiv 1 - \frac{r^2}{2d}, \quad (4.95)$$

where r is the magnitude $|p(k)|$ of the lattice momentum. Note that, since $c(k)$ takes values in the interval $(-1/2, 1/2]$, we have $\cos[\theta(k)/2] \in (-1, 1]$, $\theta(k) \in [0, 2\pi)$ and $r \in [0, 2\sqrt{d}]$. Thus, we can rewrite this eigenvalue as

$$\lambda(r, P) = \frac{P^2 \left(1 - \frac{r^2}{2d}\right)^2}{1 + (P^2 - 1) \left(1 - \frac{r^2}{2d}\right)^2}. \quad (4.96)$$

It is easy to check that

- $\lambda(r, P) = 1$ for $r = 0$,
- the derivative of $\lambda(r, P)$ with respect to r is zero for $r = 0$ and $r = \sqrt{2d}$,
- this derivative is negative (respectively positive) for $r < \sqrt{2d}$ (respectively for $r > \sqrt{2d}$).

In Fig. 1 we plot $\lambda(r, P)$ as a function of r for the case $d = 4$ and $P = 0.2$. We note that the eigenvalue $\lambda(r, P)$ does not show the oscillatory behavior that can be observed when one considers a probability distribution that is uniform¹⁰ for m in the interval $[1, 2\overline{m} - 1]$ (see Figs. 1 and 2 in Ref. [9]). Also note that this eigenvalue is close to 1 for small momenta $r \approx 0$ and for very large momenta, i.e. with $r \approx 2\sqrt{d}$, and that in both cases we have $c^2(k) \approx 1/4$ and $\cos^2[\theta(k)/2] \approx 1$. As explained at the end of Section 4, this is a natural consequence of the even/odd updating scheme.

¹⁰ Note that with this distribution we automatically have $\langle m \rangle$ equal to $\overline{m}$.

It follows that $\max_{k \neq 0} \lambda(k, P) < 1$ is obtained for $c^2(k) \approx 1/4$. Then, using eqs. (4.31) and (4.75) we have, in the limit of large lattice side N ,

$$\cos^2[\theta(k)/2] = 4c^2(k) \approx 1 - 2\zeta(N) \quad (4.97)$$

and from eq. (4.94) we find

$$\lambda(k, P) \approx 1 - \frac{2\zeta(N)}{P^2}. \quad (4.98)$$

Thus, $\lambda(k, P)$ is very close to 1 and we obtain

$$\frac{\tau}{\langle m \rangle + 1} \approx \frac{1}{1 - \max_{k \neq 0} \lambda(k, P)}. \quad (4.99)$$

Using again eq. (4.94) and eq. (4.97) we get

$$1 - \max_{k \neq 0} \lambda(k, P) \approx \frac{2\zeta(N)}{2\zeta(N)(1 - P^2) + P^2}, \quad (4.100)$$

so that¹¹

$$\frac{\tau}{\langle m \rangle + 1} \approx \left(1 - P^2\right) + \frac{P^2}{2\zeta(N)}. \quad (4.101)$$

Also, from eqs. (4.86) and (4.93), we have

$$\langle m \rangle = \frac{p}{1 - p} = \frac{1 - P}{2P} \quad (4.102)$$

and

$$\langle m \rangle + 1 = \frac{1 + P}{2P}. \quad (4.103)$$

These equations give

$$\tau \approx \left[\left(1 - P^2\right) + \frac{P^2}{2\zeta(N)} \right] \frac{1 + P}{2P}. \quad (4.104)$$

We can now fix P by minimizing the value of τ . In this way we obtain

$$P^2 = \frac{2\zeta(N)}{[1 - 2\zeta(N)](1 + 2P)} \approx \frac{2\zeta(N)}{(1 + 2P)}. \quad (4.105)$$

Therefore, in the limit of large lattice side N , we get that P goes to zero (and p goes to 1) as

$$P \approx \sqrt{2\zeta(N)} = \frac{2\pi}{\sqrt{d}N} \quad (4.106)$$

and

$$\tau_{stoc} \approx \left[1 + \frac{P^2}{2\zeta(N)} \right] \frac{1}{2P} \approx \frac{1}{P} \approx \frac{\sqrt{d}N}{2\pi}. \quad (4.107)$$

¹¹ Since at this point we don't know the relation between P and $\zeta(N)$ we have to keep all terms in this equation.

Thus, as expected, we have $z = 1$. Let us notice that the tuning for P given in eq. (4.106) coincides with the tuning for Ω obtained in eq. (4.59) for the overrelaxation algorithm. Also we have

$$p = \frac{1 - P}{1 + P} \approx 1 - 2P = 1 - \frac{4\pi}{\sqrt{d}N} \quad (4.108)$$

and

$$1 + p = \frac{2}{1 + P} \approx \frac{2}{1 + \Omega} = \omega, \quad (4.109)$$

namely we find the relation $p \approx \omega - 1$. This is in agreement with the result obtained analytically and numerically in two dimensions at finite β (see Sections 5 and 7.3 in Ref. [4]).

Finally, if we do **not** tune the value of the parameter P (or equivalently of the parameter p) then we have again two limiting cases. In fact, if P is very small and such that

$$P^2 < 2\zeta(N) \quad (4.110)$$

then from eq. (4.104) we obtain

$$\tau \approx \frac{1}{2P}, \quad (4.111)$$

namely the relaxation time is constant in N and $z = 0$. On the contrary, if P is large and

$$P^2 > 2\zeta(N), \quad (4.112)$$

then we find

$$\tau \approx \frac{1 + P}{2P} \frac{P^2}{2\zeta(N)} = \frac{(1 + P)P}{2} \frac{dN^2}{4\pi^2} \quad (4.113)$$

and [using eq. (4.38)]

$$\tau \approx \frac{(1 + P)P}{2} \tau_{LosAlamos}. \quad (4.114)$$

This gives a dynamic critical exponent z equal to 2. However, in this case, the improved local algorithm without tuning works better than the Los Alamos method: the relaxation time τ given in eq. (4.114) is always smaller [for $P \in (0, 1)$] than the Los Alamos relaxation time. As in the overrelaxation case, when N goes to infinity (with P fixed) we always get (4.113) and find $z = 2$. Also, this analysis implies that the dynamic critical exponent z depends only on the relation between P^2 and $2\zeta(N)$. In fact, if we set P^2 much smaller than, equal to, or much larger than $2\zeta(N)$ we have that the dynamic critical exponent z is equal to 0, 1 or 2 respectively.

5 Generalized Local Algorithms

In Sections 2, 3 and 4 we have studied CSD for two main types of local algorithms: the overrelaxation algorithm — which coincides with the Los Alamos algorithm for $\omega = 1$ and with the Cornell algorithm with the choice [see eq. (3.23)] $\omega \approx \alpha \mathcal{N}(y)$ — and the stochastic overrelaxation algorithm. In both cases we have seen that with a careful tuning (of the parameters ω and p respectively) we obtain a dynamic critical exponent $z = 1$. In this section we want to see if it is possible to generalize these algorithms in order to get $z < 1$. To the best of our knowledge, the results presented in Sections 5.2 and 5.3 below are new.

5.1 Generalized Overrelaxation Algorithm

Let us consider the following generalization of the standard overrelaxation update [see eq. (2.3)]

$$g^{(linear)}(x) \equiv \frac{a(\omega) \tilde{h}^\dagger(x) + b(\omega) g(x)}{\sqrt{[a(\omega) + b(\omega)]^2 - a(\omega) b(\omega) [2 - \mathcal{T}(x)]}} . \quad (5.1)$$

One can check that $g^{(linear)}(x) \in SU(2)$ and that the overrelaxation update corresponds to the choices $a(\omega) = \omega$ and $b(\omega) = 1 - \omega$. In the limit of large number of gauge-fixing sweeps t [see Section 3] we can use eq. (3.12) and obtain

$$g^{(linear)}(x) \approx \frac{a(\omega)}{|a(\omega) + b(\omega)|} \tilde{h}^\dagger(x) + \frac{b(\omega)}{|a(\omega) + b(\omega)|} g(x) , \quad (5.2)$$

where terms of order ϵ^2 have been neglected. This update can be written in the simpler form¹²

$$g^{(linear)}(x) \approx a(\omega) \tilde{h}^\dagger(x) + b(\omega) g(x) \quad (5.3)$$

if we assume the condition $a(\omega) + b(\omega) = 1$ or, equivalently, by a redefinition of the coefficients $a(\omega)$ and $b(\omega)$. Finally, using eq. (3.4), we find the update for the $\vec{f}(x)$ field

$$\vec{f}^{(linear)}(x) = a(\omega) \vec{f}^{(LosAl.)}(x) + b(\omega) \vec{f}(x) . \quad (5.4)$$

If we consider the dependence of the massless-free-field action on the value of the field $\vec{f}$ at a given site y [see eqs. (3.21) and (3.22)], it is clear that this is the most general local linear update (with site-independent coefficients) of the field $\vec{f}(y)$. One can also check that the condition $b^2(\omega) < 1$ is sufficient to prove that the update (5.4) never increases the value of the massless-free-field action [see eq. (3.22)]. Since the definition of ω is in principle arbitrary, we can at this point set $a(\omega) = \omega$ and obtain that the standard overrelaxation algorithm is the most general local linear update with site-independent coefficients. Therefore, following the analysis presented in the previous section we have at best that $z = 1$.

In order to understand why, in this case, one cannot get a dynamic critical exponent z smaller than 1, we can follow Ref. [10] and consider the inequality [see eq. (3.35)]

$$\tau \geq \frac{1}{\min_{k \neq 0} |1 - \lambda_\pm(k, \omega)|} . \quad (5.5)$$

When $r^2(k, \omega) \leq 1$, namely when these eigenvalues are complex, one finds [see eqs. (4.40) and (4.41)]

$$|1 - \lambda_\pm(k, \omega)| = \omega \sqrt{1 - 4c^2(k)} . \quad (5.6)$$

Since the tuning condition, i.e. $r^2(k, \omega) \leq 1$, is equivalent to the relation [see eq. (4.53)]

$$\Omega \leq \sqrt{1 - 4c^2(k)} \quad (5.7)$$

[where the inequality becomes an equality for the largest value of $c^2(k) < 1/4$], we have [using eq. (4.51)]

$$\min_{k \neq 0} |1 - \lambda_\pm(k, \omega)| = \frac{2\Omega}{1 + \Omega} . \quad (5.8)$$

¹² We have considered this type of update also in Section 5 of Ref. [4].

In the limit of large N this implies [see eq. (4.31)]

$$\Omega \lesssim \sqrt{2\zeta(N)} \quad (5.9)$$

and

$$\min_{k \neq 0} |1 - \lambda_{\pm}(k, \omega)| \approx 2\sqrt{2\zeta(N)} = \frac{4\pi}{\sqrt{d}N}, \quad (5.10)$$

so that [in agreement with eq. (4.60)]

$$\tau \approx \frac{\sqrt{d}}{4\pi} N, \quad (5.11)$$

which gives $z = 1$.

Equations (5.6) and (5.10) are the starting point of Ref. [10] (see their Fig. 1). The idea in that article is that one should look for an update characterized by a matrix $C(k)$ whose eigenvalues $\lambda(k)$ satisfy, in the limit of large N , the relation

$$\min_{k \neq 0} |1 - \lambda(k)| \propto \left(\frac{4\pi^2}{dN^2} \right)^{1/m} \quad (5.12)$$

with $m > 2$. In fact, this would imply

$$\tau \sim N^{2/m}, \quad (5.13)$$

namely $z < 1$. From eq. (4.41) it is clear that we have $m = 2$, and therefore $z = 1$, because the eigenvalues $\lambda_{\pm}(k, \omega)$ are solutions of a quadratic equation, i.e. because $C(k, \omega)$ is a 2×2 matrix. What is proven in Ref. [10] is that, unfortunately, we cannot get $m > 2$ because any general update matrix C can be shown to be block-diagonal with blocks of size not larger than 2×2 . In the next section we will consider explicitly local algorithms characterized by updating matrices of size 4×4 and we will check that we cannot obtain z smaller than 1 in that case.

5.2 A 4×4 Updating Matrix

Following what was done in Section 4, we consider here the update (4.1) and the Fourier-like transformation defined in eq. (4.20) and generalize that procedure in a way that produces an updating matrix that is 4×4 instead of 2×2 . To this end, let us recall that if the vector T has components $T_{\mu} = 1/2$ for all μ [see eq. (4.6)] then we have

$$1 + \exp(-2\pi i T \cdot x) = \begin{cases} 2 & \text{if } |x| \text{ is even} \\ 0 & \text{if } |x| \text{ is odd} \end{cases} \quad (5.14)$$

$$1 - \exp(-2\pi i T \cdot x) = \begin{cases} 0 & \text{if } |x| \text{ is even} \\ 2 & \text{if } |x| \text{ is odd} \end{cases} \quad (5.15)$$

These two linear combinations automatically select the even and odd sub-lattices and can be used to construct the two-component field $f^{b,\pm}(k)$ [see eq. (4.20)]. Let us notice that one can also rewrite the above relations as

$$\exp(-2\pi i T_1 \cdot x) \pm \exp(-2\pi i T_2 \cdot x) \quad (5.16)$$

with $T_{1,\mu} = 1$ and $T_{2,\mu} = 1/2$ for all μ . We can easily generalize this result and divide the lattice in, for example, four sub-lattices.¹³ In fact with $T_{1,\mu} = 1$, $T_{2,\mu} = 1/2$, $T_{3,\mu} = 3/4$ and $T_{4,\mu} = 1/4$ we have that the linear combinations

$$L_{ee}(x) = e^{(-2\pi i T_1 \cdot x)} + e^{(-2\pi i T_2 \cdot x)} + e^{(-2\pi i T_3 \cdot x)} + e^{(-2\pi i T_4 \cdot x)} \quad (5.17)$$

$$L_{eo}(x) = e^{(-2\pi i T_1 \cdot x)} + e^{(-2\pi i T_2 \cdot x)} - e^{(-2\pi i T_3 \cdot x)} - e^{(-2\pi i T_4 \cdot x)} \quad (5.18)$$

$$L_{oe}(x) = e^{(-2\pi i T_1 \cdot x)} - e^{(-2\pi i T_2 \cdot x)} + i e^{(-2\pi i T_3 \cdot x)} - i e^{(-2\pi i T_4 \cdot x)} \quad (5.19)$$

$$L_{oo}(x) = e^{(-2\pi i T_1 \cdot x)} - e^{(-2\pi i T_2 \cdot x)} - i e^{(-2\pi i T_3 \cdot x)} + i e^{(-2\pi i T_4 \cdot x)}, \quad (5.20)$$

called respectively even-even, even-odd, odd-even and odd-odd, are always zero but for the following cases

$$L_{ee}(x) = 4 \quad \text{if } |x| \bmod 4 = 0 \quad (5.21)$$

$$L_{eo}(x) = 4 \quad \text{if } |x| \bmod 4 = 2 \quad (5.22)$$

$$L_{oe}(x) = 4 \quad \text{if } |x| \bmod 4 = 1 \quad (5.23)$$

$$L_{oo}(x) = 4 \quad \text{if } |x| \bmod 4 = 3. \quad (5.24)$$

Thus, in this way we can automatically divide the lattice in four sub-lattices and define a four-component field $(f_{ee}^a(k), f_{eo}^a(k), f_{oe}^a(k), f_{oo}^a(k))$ by

$$f_{ee}^a(k) \equiv \sum_x f^a(x) L_{ee}(x) \exp(-2\pi i k \cdot x), \quad (5.25)$$

and analogously for the other three components. Also, in analogy with eqs. (4.21) and (4.22), one can check that

$$\sum_x f^a(x + e_\mu) L_{ee}(x) \exp(-2\pi i k \cdot x) = e^{+2\pi i k_\mu} f_{ee}^a(k) \quad (5.26)$$

$$\sum_x f^a(x - e_\mu) L_{ee}(x) \exp(-2\pi i k \cdot x) = e^{-2\pi i k_\mu} f_{ee}^a(k) \quad (5.27)$$

and similarly using the other linear combinations defined in eqs. (5.18)–(5.20). Then, for any updating sequence of the four components $(f_{ee}^a(k), f_{eo}^a(k), f_{oe}^a(k), f_{oo}^a(k))$ we obtain an updating matrix which is 4×4 . For example, if we update these components in the order even-even, even-odd, odd-even and odd-odd one can verify that the updating matrix is given by¹⁴

$$(1 - \omega) \mathbb{1} + \omega \begin{pmatrix} 0 & E^-(k) \\ (1 - \omega) E^+(k) & \omega E^+(k) E^-(k) \end{pmatrix}, \quad (5.28)$$

where $\mathbb{1}$ is the 4×4 identity matrix and $E^\pm(k)$ are 2×2 matrices defined by

$$E^\pm(k) \equiv \begin{pmatrix} e^\pm(k) & e^\mp(k) \\ e^\mp(k) & e^\pm(k) \end{pmatrix} \quad (5.29)$$

¹³ In this section, in order to simplify the notation, we suppose that the lattice side N is a multiple of 4.

¹⁴ In order to avoid over-counting for the momenta we should set, for example, $k_d N = 0, 1, \dots, N/4 - 1$ and $k_i N = 0, 1, \dots, N - 1$ for $i = 1, \dots, d - 1$.

with

$$e^\pm(k) \equiv \frac{1}{2d} \sum_{\mu=1}^d e^{\pm 2\pi i k_\mu} \equiv e_r(k) \pm i e_i(k). \quad (5.30)$$

Clearly the matrix in eq. (5.28) has a structure very similar to that of the 2×2 matrix given in eq. (4.24). In fact, in this case, we are still using a checkerboard ordering (first all even sites and then all odd sites), but with the even and odd sub-lattices divided in turn into two sub-lattices. The eigenvalues of this 4×4 matrix are, as expected from Ref. [10], solutions of two different second-order equations and are given by

$$\lambda_\pm^r(k, \omega) = (1 - \omega) + 2\omega^2 e_r^2(k) \pm 2\omega \sqrt{(1 - \omega)^2 e_r^2(k) + \omega^2 e_r^4(k)} \quad (5.31)$$

$$\lambda_\pm^i(k, \omega) = (1 - \omega) + 2\omega^2 e_i^2(k) \pm 2\omega \sqrt{(1 - \omega)^2 e_i^2(k) + \omega^2 e_i^4(k)}. \quad (5.32)$$

Since $e_r(k)$ is equal to the quantity $c(k)$ defined in eq. (4.8), we have that the eigenvalues $\lambda_\pm^r(k, \omega)$ coincide with the two eigenvalues of the overrelaxation method obtained in Section 4. Also, for $\omega = 1$, we have $\lambda_\pm^{r,i}(k, \omega) = 0, 4e_{r,i}^2(k)$ and $4e_r^2(k) = 4c^2(k)$ is the non-zero eigenvalue of the Los Alamos method found in Section 4.1. We note that

$$e_i(k) = \frac{1}{2d} \sum_{\mu=1}^d \sin(2\pi k_\mu) \quad (5.33)$$

assumes its largest value (equal to $1/2$) when $k_\mu = 1/4$ (for all directions μ). This implies [see eqs. (5.31) and (5.32)] that CSD is now due not only to the long-wavelength modes — i.e. small momenta $p^2(k) \approx 0$, for which $4c^2(k) \approx 1$ — but also to the modes with $k_\mu \approx 1/4$, corresponding to momenta $p^2(k) \approx 2d$ and for which $4e_i^2(k) \approx 1$. This result can be explained by observing that the division of the lattice in four sub-lattices couples the modes with $k_\mu \approx 0$ to the modes with $k_\mu \approx 1/4$. In fact, $e_i(k)$ becomes $e_r(k) = c(k)$ when k_μ goes to $k_\mu + 1/4$ (for all directions μ).

Of course, if one considers a different updating sequence for the four components of the field $f^a(k)$, then the updating matrix will be different from that reported in eq. (5.28). For example, if we update these components in the order even-even, odd-even, even-odd and odd-odd one can verify that the updating matrix is given by

$$\mathcal{M}_4 = \begin{pmatrix} (1 - \omega) & 0 & \omega e^-(k) & \omega e^+(k) \\ (1 - \omega)\omega^2 e^{+2}(k) & f(k, \omega) & \omega e^+(k) f(k, \omega) & g(k, \omega) \\ (1 - \omega)\omega e^+(k) & \omega e^-(k) & f(k, \omega) & \omega^2 e^{+2}(k) \\ (1 - \omega)g(k, \omega) & \omega e^+(k) f(k, \omega) & h(k, \omega) & f(k, \omega) + \omega e^+(k) g(k, \omega) \end{pmatrix}, \quad (5.34)$$

where

$$f(k, \omega) \equiv (1 - \omega) + \omega^2 e^+(k) e^-(k) \quad (5.35)$$

$$g(k, \omega) \equiv \omega e^-(k) + \omega^3 e^{+3}(k) \quad (5.36)$$

$$h(k, \omega) \equiv \omega^2 [e^{-2}(k) + e^{+2}(k) f(k, \omega)]. \quad (5.37)$$

In this case we were not able to prove that the characteristic equation of the above 4×4 matrix can be factorized in two different second-order equations and we could not find any simple expression for the four eigenvalues. [On the other hand, from (5.34) it is obvious that one of the eigenvalues of the matrix $\mathcal{M}_4$ is zero when $\omega = 1$.] However, after some manipulations one can verify that the characteristic equation of $\mathcal{M}_4$ can be factorized into two “almost” second-order equations given by

$$(1 - \omega - \lambda)^2 - 2\omega^2 \lambda e^+(k) e^-(k) \pm \sqrt{\lambda} \omega^2 [e^{-2}(k) + \lambda e^{+2}(k)] = 0. \quad (5.38)$$

By using eq. (5.30) and the relation $e_r(k) = c(k)$ one can re-write the above equations as

$$(1 - \omega - \lambda)^2 - 4\omega^2 \lambda c^2(k) + \sqrt{\lambda} \omega^2 \left[c^2(k) (1 + \sqrt{\lambda})^2 - e_i^2(k) (1 + \sqrt{\lambda})^2 - 2i c(k) e_i(k) (1 - \lambda) \right] = 0 \quad (5.39)$$

and

$$(1 - \omega - \lambda)^2 - 4\omega^2 \lambda c^2(k) - \sqrt{\lambda} \omega^2 \left[c^2(k) (1 - \sqrt{\lambda})^2 - e_i^2(k) (1 - \sqrt{\lambda})^2 - 2i c(k) e_i(k) (1 - \lambda) \right] = 0. \quad (5.40)$$

Let us notice that, written in this way, these two equations are very similar to the characteristic equation of the matrix $M(k, \omega)$ given in eq. (4.24) [or equivalently of the matrix $C(k, \omega)$ given in eq. (4.16)]:

$$(1 - \omega - \lambda)^2 - 4\omega^2 \lambda c^2(k) = 0. \quad (5.41)$$

Before considering the equations (5.39) and (5.40) it is interesting to study in more detail eq. (5.41) and see how we can estimate the dynamic critical exponent z . To this end we can re-write the previous equation as

$$\left[(1 - \lambda) - \omega \sqrt{1 - 4c^2(k)} \right]^2 + 2\omega (1 - \lambda) \left\{ \sqrt{1 - 4c^2(k)} - [1 - 2\omega c^2(k)] \right\} = 0 \quad (5.42)$$

and for the largest value of $c^2(k) < 1/4$, in the limit of large lattice side N , we obtain [using eq. (4.31)]

$$\left[(1 - \lambda) - \omega \sqrt{2\zeta(N)} + \mathcal{O}(\zeta^{3/2}(N)) \right]^2 + 2\omega (1 - \lambda) \left\{ \sqrt{2\zeta(N)} - \left(1 - \frac{\omega}{2} \right) + \mathcal{O}(\zeta(N)) \right\} = 0. \quad (5.43)$$

Then by setting $\lambda = 1 - \delta$ we get

$$\delta^2 + 2\omega^2 \zeta(N) + 2\omega \delta \left(\frac{\omega}{2} - 1 \right) + \mathcal{O}(\delta \zeta(N), \zeta^2(N)) = 0. \quad (5.44)$$

Thus, if we do not tune the parameter ω we have that δ is the solution of the equation

$$\omega \zeta(N) + \delta \left(\frac{\omega}{2} - 1 \right) + \mathcal{O}(\delta^2, \delta \zeta(N), \zeta^2(N)) = 0, \quad (5.45)$$

namely $\delta \propto \zeta(N) \sim 1/N^2$. This implies [see end of Section 3]

$$\tau \gtrsim \frac{1}{|\delta|} \sim N^2 \quad (5.46)$$

and $z = 2$. On the contrary if we tune $\omega = 2/(1 + \Omega)$ by setting

$$\Omega = \overline{\Omega} \zeta^m(N), \quad (5.47)$$

with $m > 0$, then from eq. (5.44) we obtain

$$\delta^2 - 4\delta\overline{\Omega}\zeta^m(N) + 8\zeta(N) + \mathcal{O}(\delta\zeta(N), \delta\zeta^{2m}(N), \zeta^{1+m}(N), \zeta^2(N)) = 0. \quad (5.48)$$

Note that for $m < 1/2$ the previous equation simplifies to

$$\delta^2 - 4\delta\overline{\Omega}\zeta^m(N) + \mathcal{O}(\delta\zeta^{2m}(N), \zeta(N)) = 0, \quad (5.49)$$

with solutions $\delta = 0$ and $\delta = 4\overline{\Omega}\zeta^m(N)$. Thus, in this case one of the eigenvalues is equal to 1 and the algorithm does not converge. On the other hand, for $m = 1/2$ we have

$$\delta^2 - 4\delta\overline{\Omega}\sqrt{\zeta(N)} + 8\zeta(N) + \mathcal{O}(\delta\zeta(N), \zeta^{3/2}(N)) = 0 \quad (5.50)$$

and the solutions δ are clearly proportional to $\sqrt{\zeta(N)}$, giving $z = 1$. One can also check that the tuning condition $\overline{\Omega} = \sqrt{2}$ [see eq. (4.55)] reduces the previous equation to a perfect square, namely

$$\left[\delta - 2\sqrt{2\zeta(N)}\right]^2 + \mathcal{O}(\delta\zeta(N), \zeta^{3/2}(N)) = 0. \quad (5.51)$$

Clearly, this analysis can also be applied to the two equations (5.39) and (5.40). In this way we will check that the dynamic critical exponent z cannot be smaller than 1 when using the updating matrix $\mathcal{M}_4$. To this end, we have to consider the largest value of $c^2(k) < 1/4$ — corresponding to $k_i = 0$ for $i = 1, \dots, d-1$ and $k_d = 1/N$ — in the limit of large lattice side N , i.e. we use eq. (4.31). For the same k , in the limit of large N , we also have the relation

$$e_i(k) = \frac{1}{2d} \sin\left(\frac{2\pi}{N}\right) \approx \frac{\pi}{dN} + \mathcal{O}(N^{-3}) = \sqrt{\frac{\zeta(N)}{2d}} + \mathcal{O}(\zeta^{3/2}(N)). \quad (5.52)$$

Then, for $N = \infty$ and by considering the equation (5.39) we get

$$(1 - \lambda)^2 + 2\omega(1 - \lambda)\left(\frac{\omega}{2} - 1\right) + \sqrt{\lambda}\frac{\omega^2}{4}(1 + \sqrt{\lambda})^2 = 0. \quad (5.53)$$

Obviously, with $\omega \in (1, 2)$ there is no solution $\lambda \approx 1$ that can satisfy this equation. In other words, if we set $\lambda = 1 - \delta$, then δ stays finite and we don't get a divergent relaxation time τ . Thus, critical slowing-down should be related to the solutions of the equation (5.40). For this equation, using eqs. (4.31) and (5.52) and setting again $\lambda = 1 - \delta$, we find

$$\begin{aligned} \left(1 - \frac{\omega^2}{16}\right)\delta^2 + 2\omega^2\zeta(N) + 2\omega\delta\left(\frac{\omega}{2} - 1\right) \\ + i\omega^2\delta\sqrt{\frac{\zeta(N)}{2d}} + \mathcal{O}(\delta^3, \delta^2\sqrt{\zeta(N)}, \delta\zeta(N), \zeta^2(N)) = 0. \end{aligned} \quad (5.54)$$

This is very similar to eq. (5.44) and we can check that the two new terms $-\omega^2 \delta^2/16$ and $i\omega^2 \delta \sqrt{\zeta(N)/(2d)}$ do not spoil the analysis already done for that equation. In fact, if we do not tune the parameter ω we have

$$\omega \zeta(N) + \delta \left(\frac{\omega}{2} - 1 \right) + \mathcal{O}(\delta^2, \delta \sqrt{\zeta(N)}, \zeta^2(N)) = 0, \quad (5.55)$$

namely $\delta \propto \zeta(N) \sim 1/N^2$ and $z = 2$. On the contrary, if we use the tuning given in eq. (5.47) and consider $0 < m < 1/2$ we have

$$\frac{3}{4} \delta^2 - 4 \delta \bar{\Omega} \zeta^m(N) + \mathcal{O}(\delta^3, \delta^2 \zeta^m(N), \delta \zeta^{2m}(N), \zeta(N)) = 0 \quad (5.56)$$

with solutions $\delta = 0$ and $\delta = 16 \bar{\Omega} \zeta^m(N)/3$. Finally, with the tuning condition (5.47) and $m = 1/2$ we have

$$\frac{3}{4} \delta^2 + 8 \zeta(N) - 4 \delta \sqrt{\zeta(N)} \left(\bar{\Omega} - \frac{i}{2d} \right) + \mathcal{O}(\delta^3, \delta^2 \sqrt{\zeta(N)}, \delta \zeta(N), \zeta^{3/2}(N)) = 0 \quad (5.57)$$

with the solution $\delta \sim \sqrt{\zeta(N)}$ and $z = 1$.

Note that one arrives at the same results by considering $k_i = 1/4$ for $i = 1, \dots, d-1$ and $k_d = 1/4 - 1/N$, corresponding to momenta $p^2(k) \approx 2d$, for which $4e_i^2(k) \approx 1$ [see comment after eq. (5.33)]. In fact, in this case, we have

$$c(k) = \sqrt{\frac{\zeta(N)}{2d}} + \mathcal{O}(\zeta^{3/2}(N)) \quad (5.58)$$

and

$$e_i(k) = \frac{1}{2} [1 - \zeta(N)] . \quad (5.59)$$

In particular, for this value of k one can verify that the equation (5.40) has solutions $\lambda = 1 - \delta$ with δ finite. Thus, the corresponding relaxation times τ do not diverge and CSD is related to the solutions of the equation (5.39), yielding z not smaller than 1.

We checked numerically these results in two, three and four dimensions at $\beta = \infty$ for several lattice sides, obtaining indeed $z = 1$ and a computational cost equivalent to that of the standard overrelaxation method. [This check was done by updating the components of the $f^a(k)$ field in the order even-even, odd-even, even-odd and odd-odd.]

To sum up we can say that with the two matrices of size 4×4 considered in this section, we cannot get a dynamic critical exponent z smaller than 1. In particular, we found that the characteristic equation of the first 4×4 matrix [see eq. (5.28)] can be factorized in two different second-order equations — as predicted in Ref. [10] — giving eigenvalues identical to those found when considering a matrix of size 2×2 [see Section 4]. For the second 4×4 matrix [see eq. (5.34)] the same factorization leads to two “almost” second-order equations and one can check that, compared to the 2×2 case, the extra term (proportional to $\sqrt{\lambda}$) does not really modify the structure of the equations. Thus, the dynamic critical exponent z must be the same in the two cases, i.e. not smaller than 1.

5.3 Generalized Stochastic Overrelaxation Algorithm

One can try to generalize the stochastic overrelaxation algorithm by considering a probability distribution different from $p^m (1 - p)$. For example, let $f(p, m)$ be the probability of having m micro-canonical sweeps [see eq. (4.72)] followed by one standard Los Alamos update. Then one has

$$\langle m \rangle \equiv \sum_{m=0}^{\infty} m f(p, m) = m(p) , \quad (5.60)$$

where we suppose that $\sum_{m=0}^{\infty} f(p, m) = 1$. (Here p is a tuning parameter or a set of tuning parameters.) Note that, if we set $f(p, m) = \delta_{m0}$ where δ_{m0} is the Kronecker delta, we obtain the Los Alamos algorithm, i.e. we don't do any micro-canonical update and $m(p) = 0$.

For this generalized stochastic overrelaxation algorithm we should consider the matrix

$$\mathcal{M}(k, p) \equiv \sum_{m=0}^{\infty} f(p, m) \widetilde{M}(k, m) \quad (5.61)$$

instead of the matrix defined in eq. (4.87). It is easy to check that this matrix is given by

$$\mathcal{M}(k, p) = \frac{\cos [\theta(k) / 2]}{\sin [\theta(k) / 2]} \begin{pmatrix} -\Sigma_1(\theta(k), p) & \Sigma_2(\theta(k), p) \\ -\cos [\theta(k) / 2] \Sigma_1(\theta(k), p) & \cos [\theta(k) / 2] \Sigma_2(\theta(k), p) \end{pmatrix} , \quad (5.62)$$

where

$$\Sigma_1(\theta(k), p) \equiv \sum_{m=0}^{\infty} f(p, m) \sin [m \theta(k)] \quad (5.63)$$

$$\Sigma_2(\theta(k), p) \equiv \sum_{m=0}^{\infty} f(p, m) \sin \left[\left(m + \frac{1}{2} \right) \theta(k) \right] . \quad (5.64)$$

The matrix $\mathcal{M}(k, p)$ has eigenvalues 0 and

$$\lambda(\theta(k), p) = \frac{\cos [\theta(k) / 2]}{\sin [\theta(k) / 2]} \{ \cos [\theta(k) / 2] \Sigma_2(\theta(k), p) - \Sigma_1(\theta(k), p) \} \quad (5.65)$$

$$= -\sin [\theta(k) / 2] \Sigma_1(\theta(k), p) + \cos^2 [\theta(k) / 2] \Sigma_3(\theta(k), p) , \quad (5.66)$$

where we define

$$\Sigma_3(\theta(k), p) \equiv \sum_{m=0}^{\infty} f(p, m) \cos [m \theta(k)] . \quad (5.67)$$

For $f(p, m) = \delta_{m0}$ we have $\Sigma_1(\theta(k), p) = 0$, $\Sigma_3(\theta(k), p) = 1$ and [using eq. (4.75)]

$$\lambda(\theta(k), p) = \cos^2 [\theta(k) / 2] = 4 c^2(k) , \quad (5.68)$$

in agreement with the result obtained for the Los Alamos algorithm in Section 4.1.

In order to study the CSD of this algorithm we should consider the largest eigenvalue of the matrix $\mathcal{M}(k, p)$. It is obvious that, if $\theta(k) = 0$ [corresponding to $c(k) = 1/2$], we have

$\Sigma_3(0, p) = 1$, $\Sigma_1(0, p) = 0$ and $\lambda(0, p) = 1$. At the same time, for a small angle $\theta(k) = \theta_s$, we can expand the above expressions in powers of θ_s and obtain¹⁵

$$\Sigma_1(\theta_s, p) = \theta_s \langle m \rangle + \mathcal{O}(\theta_s^3) \quad (5.69)$$

$$\Sigma_3(\theta_s, p) = 1 - \frac{\theta_s^2}{2} \langle m^2 \rangle + \mathcal{O}(\theta_s^4) \quad (5.70)$$

$$\lambda(\theta_s, p) = 1 - \frac{\theta_s^2}{2} \left(\langle m \rangle + \langle m^2 \rangle + \frac{1}{2} \right) + \mathcal{O}(\theta_s^4), \quad (5.71)$$

where $\langle m \rangle$ and $\langle m^2 \rangle$ are, in general, functions of p . This implies

$$\frac{\tau}{\langle m \rangle + 1} \approx \frac{1}{1 - \lambda(\theta_s, p)} \approx \frac{1}{\theta_s^2} \frac{2}{\langle m \rangle + \langle m^2 \rangle + \frac{1}{2}}. \quad (5.72)$$

From eqs. (4.31) and (4.75) and the relation $\theta(k) = \theta_s$ we have that

$$\theta_s^2 \approx 8 \zeta(N) = \frac{16\pi^2}{dN^2}. \quad (5.73)$$

Thus, if $\langle m \rangle$ and $\langle m^2 \rangle$ stay finite we have that $\tau \propto N^2$ and $z = 2$. In order to reduce CSD we have to tune p so that both $\langle m \rangle$ and $\langle m^2 \rangle$ go to infinity as powers of $1/\theta_s$. Note that if by tuning p we have that $\langle m \rangle$ goes to infinity, then from the inequality $\langle m \rangle \leq \langle m^2 \rangle$, which is a consequence of the positiveness of the variance $\sigma^2 = \langle m^2 \rangle - \langle m \rangle^2$, we get that $\langle m^2 \rangle$ goes to infinity too. The same inequality allows, in principle, $\langle m^2 \rangle$ to go to infinity while $\langle m \rangle$ stays finite, but this cannot happen if σ^2 is finite. Moreover, if $\sigma^2 < +\infty$ and $\langle m \rangle \sim \theta_s^{-n}$ we should have that $\langle m^2 \rangle \sim \theta_s^{-2n}$ and we obtain

$$\tau \approx \frac{2}{\theta_s^2} \frac{1}{1 + \frac{\langle m^2 \rangle}{\langle m \rangle}} \approx \frac{2}{\theta_s^{2-n}}. \quad (5.74)$$

From eqs. (5.69) and (5.70) and from the fact that $\Sigma_1(\theta(k), p)$ and $\Sigma_3(\theta(k), p)$ are finite,¹⁶ we obtain that — at least to order θ_s^2 — the only tuning we can have is given by

$$\langle m \rangle \sim \theta_s^{-1} \quad \langle m^2 \rangle \sim \theta_s^{-2}, \quad (5.75)$$

which implies [see eq. (4.107)]

$$\tau \approx \frac{2}{\theta_s} \approx \frac{\sqrt{d}N}{2\pi}. \quad (5.76)$$

This yields, as expected, $z = 1$. Thus, with an appropriate choice of the distribution $f(p, m)$ and of the tuning, one can only hope to reduce the factor that multiplies $1/\theta_s \approx \sqrt{d}N/\pi$ in the above equation, but there is no way of having $z < 1$.

We can verify the tuning relations

$$\langle m^2 \rangle \sim \langle m \rangle^2 \sim N^2 \quad (5.77)$$

¹⁵ A similar analysis can be done for the case $\theta(k) = 2\pi - \theta_s$, with θ_s small, corresponding to $c(k) \approx -1/2$.

¹⁶ Actually, from eqs. (5.63) and (5.67), from the relation $f(p, m) \geq 0$ and the normalization condition for the probability distribution $f(p, m)$ we have that $|\Sigma_1(\theta(k), p)|$ and $|\Sigma_3(\theta(k), p)|$ are smaller than or equal to 1.

for the probability distribution $f(p, m) = p^m(1 - p)$, which has a tuning condition $P \sim 1/N$ (see Section 4.3), and for the probability distribution $f(p, m)$ constant in the interval $[1, 2\overline{m} - 1]$, which has a tuning condition $\overline{m} \sim N$ (see Ref. [9]). In the first case we know that

$$\langle m \rangle = \frac{1 - P}{2P} \quad (5.78)$$

and one can check that

$$\langle m^2 \rangle = \frac{p(1 + p)}{(1 - p)^2} = \frac{1 - P}{2P^2}. \quad (5.79)$$

Thus, when P goes to zero as $1/N$, relations (5.77) are satisfied. In the second case we have that the average value of m is $\overline{m}$ and one can verify that

$$\langle m^2 \rangle = \frac{\overline{m}}{3} (4\overline{m} - 1). \quad (5.80)$$

Thus, when $\overline{m}$ goes to infinity as N we obtain again relations (5.77).

Let us notice that the analysis presented in Ref. [10] clearly applies also to the stochastic overrelaxation algorithm for any probability distribution $f(p, m)$, as long as the updating matrix $\mathcal{M}(k, p)$ is 2×2 . So, the result that z cannot be smaller than 1 for the generalized stochastic overrelaxation algorithm given by the matrix (5.62) is not unexpected. However, we believe that the previous analysis, and especially the relations in eq. (5.75), clarify how critical slowing-down is reduced by this algorithm.

6 Numerical Results

In order to check the analytical predictions presented in the previous sections we have done numerical tests in two, three and four dimensions. In each case we considered eight different lattice sides N , namely $N = 16, 32, 48, \dots, 128$ in two dimensions, $N = 8, 16, 24, \dots, 64$ in three dimensions and $N = 4, 8, 12, \dots, 32$ in four dimensions. Also, for all the algorithms we have done tests using both the lexicographic and the even/odd update. For the Fourier acceleration method only lattice sides that are powers of 2 were considered and we used either the whole lattice or even/odd sublattices to implement the Laplacian preconditioning.

Simulations were done on the PC cluster installed in July 2001 at the IFSC-USP in connection with a grant from FAPESP (“Projeto Jovem Pesquisador”). The system has 16 nodes and a server with 866 MHz Pentium III CPU and 256/512 MB RAM memory (working at 133 MHz) and is operating with Linux Debian. The machines are connected with a 100 Mbps full-duplex network. The total computer time used for the tests (including the runs described in Sections 5.2, 6.3, 6.4 and 7) was equivalent to about 100 days on one node.

In Ref. [4] we checked the convergence of the gauge-fixing algorithms by considering six different quantities. We found that, for each given algorithm, these quantities relax to zero with the same speed, i.e. the same relaxation time. Here we consider only two of these six quantities, namely¹⁷

$$(\nabla A)^2 \equiv \frac{1}{V} \sum_x \sum_{c=1}^3 \left[(\nabla \cdot A^c)(x) \right]^2, \quad (6.1)$$

¹⁷ In Ref. [4] these two quantities were called, respectively, e_2 and e_6 .

which is commonly used in numerical simulations, and

$$\Sigma_Q \equiv \frac{1}{d} \sum_{\mu=1}^d \frac{1}{3N} \sum_{c=1}^3 \sum_{x_\mu=1}^N \left[Q_\mu^c(x_\mu) - \overline{Q}_\mu^c \right]^2 \left[\overline{Q}_\mu^c \right]^{-2}, \quad (6.2)$$

which provides a very sensitive test of the goodness of the gauge fixing [4]. Let us recall that we defined the lattice gauge field as [see eq. (2.13)]

$$A_\mu(x) \equiv \frac{1}{2} \left[U_\mu(x) - U_\mu^\dagger(x) \right] \quad (6.3)$$

and that [see eq. (2.12)]

$$(\nabla \cdot A^c)(x) \equiv \sum_{\mu=1}^d \left[A_\mu^c(x) - A_\mu^c(x - e_\mu) \right] \quad (6.4)$$

is the lattice divergence of

$$A_\mu^c(x) \equiv \frac{1}{2i} \text{Tr} [A_\mu(x) \sigma^c], \quad (6.5)$$

where σ^c is a Pauli matrix and $c = 1, 2, 3$. We also define

$$\overline{Q}_\mu^c \equiv \frac{1}{N} \sum_{x_\mu=1}^N Q_\mu^c(x_\mu), \quad (6.6)$$

where the quantities

$$Q_\mu^c(x_\mu) \equiv \sum_{\nu \neq \mu} \sum_{x_\nu} A_\mu^c(x) \quad \mu = 1, \dots, d \quad (6.7)$$

are constant, i.e. independent of x_μ , if the Landau-gauge-fixing condition is satisfied [4]. Let us notice that, at $\beta = \infty$ and at a minimum of $\mathcal{E}_U[g]$, one has $\overline{Q}_\mu^c = 0$. Therefore at $\beta = \infty$ the quantity Σ_Q should be defined as

$$\Sigma_Q \equiv \frac{1}{d} \sum_{\mu=1}^d \frac{1}{3N} \sum_{c=1}^3 \sum_{x_\mu=1}^N \left[Q_\mu^c(x_\mu) \right]^2. \quad (6.8)$$

We used $(\nabla A)^2 \leq 10^{-15}$ as stopping condition for the gauge-fixing algorithms. The quantity Σ_Q and the minimizing functional $\mathcal{E}_U[g]$ have been evaluated only for the final gauge-fixed configuration.

Let us notice that, using eq. (2.18), we can re-write $(\nabla A)^2$ as

$$(\nabla A)^2 = \frac{1}{V} \sum_x \sum_{c=1}^3 [\mathbf{w}^c(x)]^2. \quad (6.9)$$

Also, from (2.6) and (2.8) we can write

$$\mathbf{w}(x) = \mathcal{N}(x) \tilde{\mathbf{w}}(x), \quad (6.10)$$

where $\tilde{w}(x)$ is an $SU(2)$ matrix, so that

$$(\nabla A)^2 = \frac{1}{V} \sum_x \mathcal{N}^2(x) \sum_{c=1}^3 [\tilde{w}^c(x)]^2. \quad (6.11)$$

At the same time we can re-write the minimizing functional [see eqs. (1.1) and (2.10)] as

$$\mathcal{E}_U[g] = 1 - \frac{1}{2dV} \sum_{\mu=1}^d \sum_x \frac{\text{Tr}}{2} \left[U_\mu^{(g)}(x) + U_\mu^{(g)\dagger}(x - e_\mu) \right] = 1 - \frac{1}{2dV} \sum_x \frac{\text{Tr}}{2} w(x) \quad (6.12)$$

and using eq. (6.10) above we have

$$\mathcal{E}_U[g] = 1 - \frac{1}{2dV} \sum_x \mathcal{N}(x) \sqrt{1 - \sum_{c=1}^3 [\tilde{w}^c(x)]^2}. \quad (6.13)$$

Then, for $\beta = \infty$ and in the limit of large number of gauge-fixing sweeps t , namely by using eq. (3.11), we obtain

$$(\nabla A)^2 = \frac{4d^2}{V} \sum_x \sum_{c=1}^3 [\tilde{w}^c(x)]^2 + \mathcal{O}(\epsilon^2) \quad (6.14)$$

and

$$\mathcal{E}_U[g] = \frac{1}{2V} \sum_x \sum_{c=1}^3 [\tilde{w}^c(x)]^2 + \mathcal{O}(\epsilon^2). \quad (6.15)$$

Thus, with the gauge fixing, $(\nabla A)^2$ goes to zero and we should find $(\nabla A)^2 \gg \mathcal{E}_U[g]$ in the final gauge-fixed configuration.

For the quantity $(\nabla A)^2(t)$, in the limit of large number of gauge-fixing sweeps t , we introduce a relaxation time τ through the relation [see eq. (3.36)]

$$(\nabla A)^2(t) \approx b \exp(-t/\tau). \quad (6.16)$$

The evaluation of τ is done using a chi-squared fit of the function $\log(\nabla A)^2(t)$. In order to get rid of the initial fluctuations, this fit has been done five times using the data corresponding to $t > n_{gf}(1 - 1/t_{fac})$, where n_{gf} is the total number of sweeps necessary to fix the gauge and $t_{fac} = 2, 4, 8, 16$ and 32 . In most cases, τ increases for increasing t_{fac} , reaching a plateau. We have chosen as the final value for τ the second point where the τ values become stable within errors.

For the algorithms depending on a parameter, and therefore requiring *tuning*, we used a procedure in three steps in order to find the optimal choice of the parameter, namely the value that minimizes the relaxation time τ at a fixed lattice side N . This procedure is similar to the one described in Ref. [4]. We considered, respectively, 5 configurations in the first step, 10 in the second and 20 in the third and final step.

Our final data for the relaxation time τ , the number of gauge-fixing sweeps n_{gf} and the time t_{gf} (measured in seconds) necessary to complete the gauge fixing are reported in Tables 1–5 for the two-, three- and the four-dimensional cases. When necessary we also report the optimal choice for the tuning parameter. For all these quantities we don't show the statistical error since it is usually very small, namely less than 1%. Recall that at $\beta = \infty$ the link variables $U_\mu(x)$ are

set equal to the identity matrix and the initial $\{g(x)\}$ configuration is chosen randomly. Also, as said in the Introduction, in the limit of large number of gauge-fixing sweeps t the configuration $U_\mu^{(g)}(x) = g(x) g^{-1}(x + e_\mu)$ is driven by the gauge fixing to the *vacuum* configuration $U_\mu^{(g)}(x) = \mathbb{1}$, losing memory of the initial $\{g(x)\}$ configuration. This explains why there are usually very small fluctuations in the quantities that one is interested in.

6.1 Critical Exponents and Computational Cost of the Algorithms

From the data shown in Tables 1–5 one can evaluate the dynamic critical exponents z for the five algorithms. In all cases — and in two, three and four dimensions — the results are in agreement with our findings in Ref. [4], namely $z \approx 2$ for the Los Alamos method, $z \approx 1$ for the three improved local algorithms and $z \approx 0$ for the Fourier acceleration method. One can also check that the total number of gauge-fixing sweeps n_{gf} grows approximately as N^z , with the same values of z given above. The time t_{gf} (measured in seconds) necessary to complete the gauge fixing grows approximately as N^{z+d} , as expected. The only exception is the Los Alamos method, for which we find $n_{gf} \sim N^{1.5}$ and $t_{gf} \sim N^{1.5+d}$, suggesting that in the initial gauge-fixing sweeps this method is more effective than the other local algorithms. This is not surprising, since it is well known [2] that the optimal strategy for the overrelaxation algorithm is precisely to vary the parameter ω from an initial value 1 (corresponding to the Los Alamos method) to a larger asymptotic value ω_{opt} . The computational cost of the Fourier acceleration method will be discussed in more detail in Section 6.4 below.

We have also looked at the values of Σ_Q , $(\nabla A)^2$ and $\mathcal{E}_U[g]$ in the final gauge-fixed configurations. We observed that:

- For all gauge-fixing algorithms and all dimensions considered one finds $\Sigma_Q > (\nabla A)^2 > \mathcal{E}_U[g]$.
- These inequalities become stronger as the lattice side N increases.
- As found in Ref. [4], the Fourier acceleration method is very efficient in relaxing Σ_Q and in this case one finds $\Sigma_Q \gtrsim (\nabla A)^2$.
- The ratio $\Sigma_Q/(\nabla A)^2$ is usually smaller (or much smaller) for the even/odd update than for the lexicographic update.
- If one uses the quantity Σ_Q to check the convergence of the gauge fixing, then the stochastic overrelaxation algorithm is better than the other local algorithms when considering the lexicographic update, in agreement with our findings in Ref. [4]. On the contrary, if one considers the even/odd update, then the quality of the gauge fixing for the Cornell method becomes almost as good as for the stochastic overrelaxation update.
- For the three improved local algorithms there is in general a gain in computational cost when using the even/odd update compared to the lexicographic update. For the Los Alamos method and the Fourier acceleration method the situation is reversed. (See next Section for a discussion of the Fourier acceleration method.)

We can conclude by saying that among the local algorithms the best appears to be the Cornell method with even/odd update. In fact, from the point of view of computational cost, this

method is equivalent to the overrelaxation algorithm and almost twice as fast as the stochastic overrelaxation algorithm. At the same time, the quality of the gauge fixing, especially when considering the relaxation of the quantity Σ_Q , is better than what is obtained with the overrelaxation algorithm and almost equivalent to the performance of the stochastic overrelaxation algorithm. Let us recall that, in the limit of large number of gauge-fixing sweeps t , the overrelaxation method and the Cornell method coincide [see eqs. (3.17), (3.18) and (3.23)] at leading order in ϵ . Therefore, the different performances of the two methods could be related to a difference in the behavior for small t . This possibility is discussed in [4, Section 7.1] and we plan to investigate it further.

6.2 Tuning of the Algorithms

In this section we check numerically the analytic predictions for the tuning of the three improved local algorithms and of the Fourier acceleration method obtained in Sections 3 and 4.

Overrelaxation method: In this case we have the tuning condition [see eqs. (4.51) and (4.59)]

$$\omega_{opt} = \frac{2}{1 + C_{opt}/N} \quad (6.17)$$

with

$$C_{opt} \approx \frac{2\pi}{d^{1/2}}. \quad (6.18)$$

In order to find the constant C_{opt} one can write

$$C_{opt} = N \frac{2 - \omega_{opt}}{\omega_{opt}}, \quad (6.19)$$

which can be used to fit the numerical data. In this way, considering the optimal choice of ω for the three largest lattice sides N , we find for the lexicographic update $C_{opt} = 5.0 \pm 0.2$ in two dimensions, 4.26 ± 0.08 in three dimensions and 3.65 ± 0.05 in four dimensions. The same fitting procedure gives $C_{opt} = 4.01 \pm 0.03$ in two dimensions, 3.63 ± 0.04 in three dimensions and 3.13 ± 0.02 in four dimensions for the even/odd update. Notice that from eq. (6.18) above, which is valid for the even/odd update, we have the analytic predictions $C_{opt} \approx 4.44$ for $d = 2$, $C_{opt} \approx 3.63$ for $d = 3$ and $C_{opt} \approx 3.14$ for $d = 4$, in good agreement with our numerical results.

Cornell method: In Ref. [4] we have found the relation

$$\omega_{opt} = \alpha_{opt} \langle \mathcal{N} \rangle = \alpha_{opt} 2d (1 - \langle \mathcal{E}_{min} \rangle), \quad (6.20)$$

where $\langle \mathcal{E}_{min} \rangle$ is the average value of the minimizing functional at the minimum. At $\beta = \infty$ one has $\langle \mathcal{E}_{min} \rangle = 0$ and the previous relation becomes $\omega_{opt} = 2d \alpha_{opt}$, in agreement with the analysis presented in Section 3 [see eqs. (3.17), (3.18) and (3.23)]. From Tables 2 and 3 one can check that this relation is very well verified by our data in the two-, three- and four-dimensional cases.

Stochastic overrelaxation method: In Section 4.3 we have seen that the tuning condition for the stochastic overrelaxation algorithm is given by [see eqs. (4.93) and (4.106)]

$$p = \frac{1 - P}{1 + P} \quad (6.21)$$

with

$$P \approx \frac{2\pi}{\sqrt{d}N}. \quad (6.22)$$

Moreover, by comparison with the overrelaxation algorithm, one can write $p \approx \omega - 1$. It is immediate to check that this relation is indeed verified by our data (see Tables 3 and 4).

Fourier acceleration: We did not discuss the tuning of this algorithm in Ref. [4]. The theoretical analysis in Section 3 gives the simple result

$$\alpha_{opt} = 1 \quad (6.23)$$

for any dimension d . In Ref. [4] we obtained — in two dimensions, at finite β and in the limit of large lattice sides N — the value $\alpha_{opt} \approx 1.28$, in qualitative agreement with (6.23). The agreement is better, as expected, at $\beta = \infty$. In fact, using the lexicographic update we find that $\alpha_{opt} = 1$ for any lattice side N and dimension d . On the contrary, using the even/odd update we have $\alpha_{opt} \approx 1.1$, with a slow decrease of α_{opt} as N increases. Also note that n_{gf} in the lexicographic case is about two times smaller than for the even/odd update. Thus, for the Fourier acceleration method, the even/odd update does not help the convergence of the algorithm. This result can be understood if one checks the size of the Fourier components of the lattice divergence $\nabla \cdot A$. In particular, one can check that with the even/odd update the slowest relaxing mode corresponds to the shortest wavelength. It is this mode that makes the Fourier acceleration method perform worse in the even/odd case. This is related to the fact that the even/odd update couples the low- and high-frequency modes [15].

6.3 Overrelaxation and Stochastic Overrelaxation without Tuning

In order to check the analytic predictions presented in Sections 4.2 and 4.3, we studied numerically the performance of the overrelaxation and of the stochastic overrelaxation algorithms also in the case without tuning. To this end, we did tests in the two dimensional case (at $\beta = \infty$ with lattice sides $N = 16, 32, 48, \dots, 128$). For both algorithms we considered the two limiting cases studied analytically, namely:

- for the overrelaxation algorithm we used $\omega = 1.98$ (corresponding to the small value $\Omega \approx 0.01$) and $\omega = 1.3$ (corresponding to $\Omega \approx 0.54$);
- for the stochastic overrelaxation we set $p = 0.96$ (namely $P \approx 0.02$) and $p = 0.3$ (corresponding to $P \approx 0.54$).

As a result we got that, for small values of Ω (respectively P), τ and n_{gf} are indeed constant in N . In particular, for the overrelaxation algorithm, we found $\tau \approx 50$ and n_{gf} of the order of 1500 – 1600 using the lexicographic update and $\tau \approx 25$ and $n_{gf} \approx 800$ using the even/odd update. For the stochastic overrelaxation we have $\tau \approx 30$ and n_{gf} of the order of 1100 using the lexicographic update and $\tau \approx 25$ and $n_{gf} \approx 900$ using the even/odd update.

For large values of Ω (respectively P), the relaxation time τ is well fitted (for both algorithms and with both types of update) by $\tau \approx 0.0136 N^z$ with $z \approx 2$. We have also checked that in this case these two algorithms (without tuning) are better than the Los Alamos method, showing a relaxation time about two times smaller.

6.4 Alternative Implementations of the Fourier Acceleration Method

In Ref. [17] we introduced a new implementation of the Fourier acceleration method, in which the inversion of the Laplacian is done using a multigrid algorithm, avoiding the use of the fast Fourier transform. This makes the method more flexible, i.e. it can efficiently work with any lattice side N and not only with N equals to a power of 2. Moreover, the new implementation is well suited for vector and parallel machines. In particular, we checked that the computational cost shows a linear speedup with the number of processors on an APE100 machine for the four-dimensional $SU(2)$ case. In that article, we have also implemented a version of the method using conjugate gradient instead of multigrid, leading to an algorithm that is efficient at intermediate lattice volumes.

In this Section we want to compare the performance of the Fourier acceleration method based on a fast Fourier transform (FFT) to the performance of the alternative implementations based on multigrid (MG) or conjugate gradient (CG) algorithms. To this end, let us recall that, even though the overhead for the MG or the CG routine is likely to be larger than the one for FFT, one can hope to reduce it by exploiting the fact that multigrid and conjugate gradient (as opposed to FFT) are iterative methods. In particular, by changing the stopping criterion for the inversion, the accuracy of the solution can be suitably varied, while for FFT the accuracy is fixed by the precision used in the numerical code. This is important, since the tuning of the parameter α is usually done only up to an accuracy of a few percent. Thus, the inversion of the Laplacian most likely will not require the high accuracy employed in the FFT case, making possible a substantial reduction of the computational cost. We checked in Ref. [17] that this is indeed the case and we found that, with an accuracy of about 10^{-5} for the inversion, one obtains an algorithm equivalent to the original one (based on FFT). For the present paper we checked again this result and found a small bug in the code previously used. After correcting it we got that the accuracy necessary for the inversion is about 10^{-3} , yielding a substantial gain with respect to the old result and in agreement with the intuitive argument above. In order to compare different implementations of the Fourier acceleration method we used here the stopping criterion

$$\frac{r_t}{r_0} \leq 10^{-3} , \quad (6.24)$$

where r_t is the magnitude of the residual after t iterations. Recall that we want to solve the equation

$$-\Delta \phi^c(x) = (\nabla \cdot A)^c(x) , \quad (6.25)$$

where $\phi^c(x)$ is the desired solution. Then, the residual is defined by

$$r^c(x) \equiv (\nabla \cdot A)^c(x) + \Delta \phi^c(x) . \quad (6.26)$$

In particular, we have tested six different implementations of the Fourier acceleration method described below, in addition to the original version (denoted by FFT-FA), based on FFT (working in single precision).

1. MG-FA: The inversion of the Laplacian is done using MG in single precision; as in Ref. [17], we used a W-cycle with 2 Gauss-Seidel sweeps before coarsening and 2 after coarsening.
2. MGCG-FA: Same as the previous algorithm, but with a CG iteration applied on the coarsest grid instead of the Gauss-Seidel iteration. This should allow larger coarsest grids, which may be useful if one wants to parallelize the code.

3. MGCGEO-FA: Same as the previous algorithm, but using a CG iteration on the coarsest grid with even/odd preconditioning.
4. CG-FA: The inversion of the Laplacian is done using CG in single precision and in the stopping criterion we compute explicitly the residual defined in eq. (6.26).
5. CGr-FA: Same as the previous algorithm, but now in the stopping criterion we use the magnitude of the residual vector built by the CG method. Note that a CG method usually stores three vectors at each step: the approximate solution x , its residual r and a search direction p .
6. CGrEO-FA: Same as the previous algorithm, but now the CG is done with even/odd preconditioning.

We used these six algorithms for numerical tests at $\beta = \infty$ in two, three and four dimensions. For the tuning parameter α we used the optimal choice obtained for the FFT-FA algorithm (see Table 5). We found that the three methods using MG are practically equivalent, with MG-FA and MGCG-FA slightly faster than MGCGEO-FA. On the contrary, among the algorithms using CG, the last one, namely CGrEO-FA, is always faster than the other two, but still slower than MG-FA and MGCG-FA. If we compare these algorithms to the original FFT-FA we see that because of the use of FFT the algorithm gets progressively worse as the lattice dimension d increases. In particular, we get that in three and in four dimensions the MG-FA algorithm is already faster for lattice sizes 32^3 and 16^4 and the gain is larger when considering the even/odd update.¹⁸ The CGrEO-FA algorithm is essentially equivalent to FFT-FA in four dimensions for lattices 16^4 or larger.

Finally, we compared the computational cost of the FFT-FA and the MG-FA algorithms with the best among the improved local methods, namely the Cornell method. In Fig. 2 we plot the CPU time needed to gauge-fix a configuration using these three methods in the four-dimensional case using even/odd update. We can see that the MG-FA method is the fastest already for the lattice volume 16^4 . This happens in three dimensions at 32^3 . We note that this analysis is very machine- and code-dependent, and that the Fourier acceleration methods are particularly well suited for the case $\beta = \infty$. As we noted in Ref. [5], the performance of the FA method is poor for small β , reaching $z = 1$ at $\beta = 0$. We are currently investigating this matter.

7 Λ Gauges

The analytic study presented in Sections 2, 3 and 4 for the Landau-gauge minimizing functional at $\beta = \infty$ — namely when all the link variables $U_\mu(x)$ are equal to the identity matrix $\mathbb{1}$ — can be easily extended to the so-called λ -gauges, which have been recently used in several analytic [18] and numerical articles [11, 19].

To this end, let us recall that a general λ -gauge can be defined by considering the minimizing

¹⁸ Note that when using the Fourier acceleration method at finite β one should avoid updating simultaneously all sites of the lattice, since the resulting move in configuration space might be too large and affect the convergence of the method.

functional

$$\mathcal{E}_{U,\lambda}[g] \equiv 1 - \frac{1}{V \left(\sum_{\mu=1}^d \lambda_{\mu} \right)} \sum_x \sum_{\mu=1}^d \lambda_{\mu} \frac{\text{Tr}}{2} \left[g(x) U_{\mu}(x) g^{\dagger}(x + e_{\mu}) \right] . \quad (7.1)$$

Clearly, if $\lambda_{\mu} = 1$ for all μ we get back the standard Landau-gauge minimizing functional given in eq. (1.2). Also, if $\lambda_i = 1$ for $i = 1, 2, \dots, d-1$, then we can interpolate [18] between the Landau and the Coulomb gauge by varying λ_d between 1 and 0.

One can easily redo all the analysis in Sections 2 and 3 and observe that all the formulae are still valid if we make the substitutions

$$\sum_{\mu=1}^d \rightarrow \sum_{\mu=1}^d \lambda_{\mu} \quad (7.2)$$

and

$$d \rightarrow \sum_{\mu=1}^d \lambda_{\mu} . \quad (7.3)$$

In particular we have

$$h(x, \lambda) \equiv \sum_{\mu=1}^d \lambda_{\mu} \left[U_{\mu}(x) g^{\dagger}(x + e_{\mu}) + U_{\mu}^{\dagger}(x - e_{\mu}) g^{\dagger}(x - e_{\mu}) \right] \quad (7.4)$$

and, after setting $U_{\mu}(x) = \mathbb{1}$,

$$\mathcal{E}_{U,\lambda}[g] = \frac{1}{2V \left(\sum_{\mu=1}^d \lambda_{\mu} \right)} \sum_x \frac{\text{Tr}}{2} \sum_{\mu=1}^d \lambda_{\mu} \left\{ [g(x) - g(x + e_{\mu})] [g(x) - g(x + e_{\mu})]^{\dagger} \right\} . \quad (7.5)$$

Also, the Laplacian Δ becomes a λ -Laplacian defined by the relation

$$\left(-\Delta_{\lambda} \vec{f} \right) (x) \equiv \sum_{\mu=1}^d \lambda_{\mu} \left[2 \vec{f}(x) - \vec{f}(x + e_{\mu}) - \vec{f}(x - e_{\mu}) \right] , \quad (7.6)$$

with eigenvalues in momentum space given by

$$p_{\lambda}^2(k) \equiv 4 \sum_{\mu=1}^d \lambda_{\mu} \sin^2(\pi k_{\mu}) . \quad (7.7)$$

Thus, the Fourier acceleration method is now a λ -Laplacian preconditioning, i.e.

$$\vec{u}(x) \equiv \left\{ \hat{F}^{-1} \left[\frac{1}{p_{\lambda}^2(k)} \hat{F} \vec{w} \right] \right\} (x) . \quad (7.8)$$

Finally, by using eq. (3.4), we can rewrite the minimizing functional (7.5) as

$$\mathcal{E}_{\lambda}[f] = \frac{\epsilon^2}{2V \left(\sum_{\mu=1}^d \lambda_{\mu} \right)} \sum_x \vec{f}(x) \cdot \left(-\Delta_{\lambda} \vec{f} \right) (x) + \mathcal{O}(\epsilon^3) , \quad (7.9)$$

which implies

$$h(x) = 2 \left(\sum_{\mu=1}^d \lambda_{\mu} \right) \mathbb{1} - i \epsilon \vec{\sigma} \cdot \sum_{\mu=1}^d \lambda_{\mu} \left[\vec{f}(x + e_{\mu}) + \vec{f}(x - e_{\mu}) \right] + \mathcal{O}(\epsilon^2) \quad (7.10)$$

$$w(x) = 2 \left(\sum_{\mu=1}^d \lambda_{\mu} \right) \mathbb{1} + i \epsilon \vec{\sigma} \cdot \sum_{\mu=1}^d \lambda_{\mu} \left[2 \vec{f}(x) - \vec{f}(x + e_{\mu}) - \vec{f}(x - e_{\mu}) \right] + \mathcal{O}(\epsilon^2) \quad (7.11)$$

and

$$\mathcal{N}(x) = 2 \left(\sum_{\mu=1}^d \lambda_{\mu} \right) + \mathcal{O}(\epsilon^2) \quad (7.12)$$

$$\vec{w}(x) = \epsilon \left(-\Delta_{\lambda} \vec{f} \right)(x) + \mathcal{O}(\epsilon^2). \quad (7.13)$$

Then, the update for the five gauge-fixing algorithms can be written as

$$\vec{f}^{(LosAl.)}(x) = \frac{1}{2 \left(\sum_{\mu=1}^d \lambda_{\mu} \right)} \sum_{\mu=1}^d \lambda_{\mu} \left[\vec{f}(x + e_{\mu}) + \vec{f}(x - e_{\mu}) \right] \quad (7.14)$$

$$\vec{f}^{(cornell)}(x) = 2 \left(\sum_{\mu=1}^d \lambda_{\mu} \right) \alpha \vec{f}^{(LosAl.)}(x) + \left[1 - 2 \left(\sum_{\mu=1}^d \lambda_{\mu} \right) \alpha \right] \vec{f}(x) \quad (7.15)$$

$$\vec{f}^{(over)}(x) = \omega \vec{f}^{(LosAl.)}(x) + (1 - \omega) \vec{f}(x) \quad (7.16)$$

$$\vec{f}^{(stoc)}(x) = \begin{cases} 2 \vec{f}^{(LosAl.)}(x) - \vec{f}(x) & \text{with probability } p \\ \vec{f}^{(LosAl.)}(x) & \text{with probability } 1 - p \end{cases} \quad (7.17)$$

$$\vec{f}^{(Fourier)}(x) = (1 - \alpha) \vec{f}(x), \quad (7.18)$$

and all the observations reported at the end of Section 3 still apply, including the relation

$$\omega = \alpha \mathcal{N}(x) + \mathcal{O}(\epsilon^2). \quad (7.19)$$

The formulae in Section 4 are also unchanged, with the only exception of eq. (4.29), which now becomes

$$c(k, \lambda) \equiv \frac{1}{2} \left[\frac{1}{\left(\sum_{\mu=1}^d \lambda_{\mu} \right)} \sum_{\mu=1}^d \lambda_{\mu} \cos(2 \pi k_{\mu}) \right] = \frac{1}{2} \left[1 - \frac{p_{\lambda}^2(k)^2}{2 \left(\sum_{\mu=1}^d \lambda_{\mu} \right)} \right]. \quad (7.20)$$

For the smallest non-zero momentum, in the limit of large lattice side N , this gives¹⁹

$$c(k(N), \lambda) \approx \frac{1}{2} \left[1 - \frac{2 \lambda \pi^2}{\left(\sum_{\mu=1}^d \lambda_{\mu} \right) N^2} \right] \equiv \frac{1}{2} [1 - \zeta(N, \lambda)], \quad (7.21)$$

¹⁹ One can check that this relation holds also for the largest momentum if one considers the absolute value of $c(k(N), \lambda)$.

where $\lambda = \min_{\mu} \lambda_{\mu}$. By using eq. (4.28) we can write

$$\zeta(N, \lambda) = \frac{\zeta(N)}{f(\lambda)} \quad (7.22)$$

with

$$f(\lambda) \equiv \frac{\sum_{\mu=1}^d \lambda_{\mu}}{d \lambda}. \quad (7.23)$$

Note that eq. (7.21) is still valid in the case of asymmetric lattices if we set

$$\frac{\lambda}{N^2} = \min_{\mu} \frac{\lambda_{\mu}}{N_{\mu}^2}. \quad (7.24)$$

It follows that the analysis of CSD and, when necessary, of the tuning of the local algorithms considered here is modified in the following way:

$$\tau_{LosAlamos}(\lambda) \approx \frac{d N^2}{4 \pi^2} f(\lambda) = \tau_{LosAlamos} f(\lambda) \quad (7.25)$$

$$\tau_{over}(\lambda) \approx \frac{1}{2 \Omega} \approx \frac{\sqrt{d} N}{4 \pi} \sqrt{f(\lambda)} = \tau_{over} \sqrt{f(\lambda)} \quad (7.26)$$

$$\tau_{stoc}(\lambda) \approx \frac{1}{P} \approx \frac{\sqrt{d} N}{2 \pi} \sqrt{f(\lambda)} = \tau_{stoc} \sqrt{f(\lambda)}. \quad (7.27)$$

Clearly, the relation $p \approx \omega - 1$ is still valid. Also, if we fix the lattice sides N , the quantity $f(\lambda)$ — and therefore the relaxation times of these algorithms — increases (respectively decreases) by decreasing (respectively increasing) the value of λ . This confirms the results obtained numerically in Ref. [11] for the cases $\lambda_i = 1$ for $i = 1, 2, 3$, and $\lambda_4 = 1$ and 0.5.

In order to verify these results we have done numerical tests in the two-dimensional case with $\lambda_1 = 1$ and $\lambda_2 = 0.25$ for the lattice sides $N = 16, 32, 48, \dots, 128$. This choice of λ 's gives $\mathcal{N}(x) \approx 1.25$ and $f(\lambda) = 2.5$. The data are reported in Tables 6–10. [Again we don't show the statistical error since it is usually very small.] By comparison with the data obtained in Landau gauge and reported in Tables 1–5, one can easily check the relations for the relaxation time τ given in eqs. (7.25)–(7.27) above. Also note that eq. (7.19) and the relation $p \approx \omega - 1$ are very well satisfied by our data.

8 Conclusions

We studied numerically and analytically five gauge-fixing algorithms in $SU(2)$ lattice gauge theory by considering the case $\beta = \infty$, for Landau gauge and λ -gauges. The analysis has been done for general dimension d and numerical checks were carried out at $d = 2, 3$ and 4. Results are in agreement with those obtained previously in Landau gauge at finite β in two dimensions [4]. In fact, we find that the (local) Los Alamos method has dynamic critical exponent $z \approx 2$, the three improved local methods we considered — the overrelaxation method, the stochastic overrelaxation method and the so-called Cornell method — have critical exponent $z \approx 1$, and the global method of Fourier acceleration completely eliminates critical slowing-down.

As said in the Introduction, if the system does not undergo a phase transition going from $\beta = 0$ to $\beta = \infty$, then the dynamic critical exponent z **should not** depend on the constant physics, i.e. it should be the same at finite β and at $\beta = \infty$. On the contrary, the constant c obtained from the fit $\tau = c N^z$ should be different in the two cases and one expects

$$c(\beta = \infty) < c(\text{finite } \beta) . \quad (8.1)$$

To make this comparison simpler, we report in Table 11 the values obtained in Ref. [4] of the constant c for the five gauge-fixing algorithms at finite β and the results of the fits done for the same algorithms at $\beta = \infty$. (In both cases we consider the lexicographic update.) From the data it is clear that the constant c satisfies very well the above inequality for the five algorithms.

Our numerical simulations show that the Cornell method with even/odd update is the best among the local algorithms. It is very fast and at the same time effective in relaxing the value of the quantity Σ_Q . It would be interesting to check if this is true also for finite β and for the $SU(3)$ case. As already observed in Ref. [4], among the local algorithms one should choose the stochastic overrelaxation method if the lexicographic update is considered. Finally, as expected, the Fourier acceleration method is extremely efficient at $\beta = \infty$ and we checked that its implementation can be improved by inverting the lattice Laplacian using a MG algorithm.

The theoretical analysis, valid for any dimension d , helped us clarify the tuning of these algorithms. In particular, the relations between the parameter ω of the overrelaxation, the parameter α of the Cornell method and the parameter p of the stochastic overrelaxation method simplify the tuning and confirm nicely the expressions obtained numerically in Ref. [4]. For the Fourier acceleration method we found analytically the tuning condition $\alpha = 1$. This result is well verified numerically at $\beta = \infty$ and at finite β (see Ref. [4]).

We also studied generalizations of the overrelaxation and of the stochastic overrelaxation algorithms. In particular, following a suggestion in [10], we considered explicitly a local algorithm (similar to overrelaxation) corresponding to an updating matrix of size larger than 2×2 (i.e. 4×4). In all cases, we verified that one cannot have a dynamic critical exponent z smaller than 1 with these local algorithms.

To sum up, in this work we have done a careful analysis of CSD for the problem of numerical gauge fixing in Landau gauge — for the $SU(2)$ group and in $d = 2, 3$ and 4 dimensions — in a case that can be studied analytically, i.e. $\beta = \infty$. This study has provided several analytic predictions, which we verified numerically. We note that at $\beta = \infty$ these results clearly apply also to the problem of numerical gauge fixing in Coulomb gauge. We believe that these predictions can be very useful in the investigation of more realistic (i.e. finite) values of β as well as for $\beta = 0$ and in the extension of this analysis to the general $SU(N)$ case.

Acknowledgments

The authors' research is supported by FAPESP, Brazil (Project No. 00/05047-5).

References

- [1] See for example L. Giusti et al., Int. J. Mod. Phys. A16 (2001) 3487.
- [2] L. Adler, Nucl. Phys. B (Proc. Suppl.) 9 (1989) 437.

- [3] U. Wolff, Nucl. Phys. B (Proc. Suppl.) 17 (1990) 93; A. D. Sokal, Nucl. Phys. B (Proc. Suppl.) 20 (1991) 55.
- [4] A. Cucchieri and T. Mendes, Nucl. Phys. B471 (1996) 263.
- [5] A. Cucchieri and T. Mendes, Nucl. Phys. B (Proc. Suppl.) 53 (1997) 811.
- [6] H.G. Dosch and V.F. Müller, Fortschr. Phys. 27 (1979) 547.
- [7] A. Hulsebos et al., Nucl. Phys. B (Proc. Suppl.) 20 (1991) 98; A. Hulsebos, M.L. Laursen and J. Smit, Phys. Lett. B291 (1992) 431; A. Hulsebos, Nucl. Phys. B (Proc. Suppl.) 30 (1993) 539.
- [8] H. Neuberger, Phys. Rev. Lett. 59 (1987) 1877.
- [9] U. Wolff, Phys. Lett. B288 (1992) 166.
- [10] G. Bathas and H. Neuberger, Phys. Rev. D45 (1992) 3880.
- [11] A. Cucchieri and T. Mendes, `hep-lat/9902024`, in the Proceedings of *Strong and Electroweak Matter '98*, Copenhagen, Denmark, 1998, edited by J. Ambjørn et al. (World Scientific, Singapore, 1999) 324.
- [12] R.G. Edwards, J. Goodman and A.D. Sokal, Nucl. Phys. B354 (1991) 289.
- [13] O. Axelsson, *Iterative Solution Methods* (Cambridge University Press, New York, 1994).
- [14] Y. Saad, *Iterative methods for sparse linear systems*, (PWS Publishing Company, Boston, 1996), postscript file available at <http://www-users.cs.umn.edu/~saad/books.html>.
- [15] I. Horvath and A.D. Kennedy, Nucl. Phys. B510 (1998) 367.
- [16] F.R. Brown and T.J. Woch, Phys. Rev. Lett. 58 (1987) 2394.
- [17] A. Cucchieri and T. Mendes, Phys. Rev. D57 (1998) R3822.
- [18] L. Baulieu and D. Zwanziger, Nucl. Phys. B548 (1999) 527.
- [19] C. Bernard et al., Nucl. Phys. B (Proc. Suppl.) 17 (1990) 593; A. Cucchieri and F. Karsch, Nucl. Phys. B (Proc. Suppl.) 83 (2000) 357; A. Cucchieri, F. Karsch and P. Petreczky, Phys. Lett. B497 (2001) 80; Nucl. Phys. B (Proc. Suppl.) 94 (2001) 385; Phys. Rev. D64 (2001) 036001.




Figure 1: Plot of the eigenvalue $\lambda(r, P)$ [see eq. (4.96)] as a function of $r = |p(k)|$ for the case $d = 4$ and $P = 0.2$.




Figure 2: Plot of the time t_{gf} (in seconds) used to complete the gauge fixing as a function of the lattice side N for the Cornell method (+), the FFT-FA algorithm ($\square$) and the MG-FA algorithm ($\bigcirc$) in four dimensions and considering even/odd update.

$V = N^d$	τ	n_{gf}	t_{gf}
16^2	6.72	177.3	0.055
32^2	26.23	587.7	0.708
48^2	58.66	1149.3	3.100
64^2	104.07	1868.2	11.200
80^2	162.43	2672.9	31.400
96^2	233.76	3661.2	61.800
112^2	318.06	4665.9	106.000
128^2	415.33	5792.1	170.000
8^3	2.59	75.5	0.067
16^3	9.95	238.5	2.580
24^3	22.13	467.6	17.800
32^3	39.16	750.7	68.200
40^3	61.05	1067.2	194.000
48^3	87.81	1420.8	467.000
56^3	119.42	1810.5	969.000
64^3	155.90	2214.9	1780.000
4^4	0.92	30.9	0.018
8^4	3.42	93.1	1.400
12^4	7.50	179.4	14.700
16^4	13.20	283.4	74.300
20^4	20.51	404.5	259.000
24^4	29.43	538.0	725.000
28^4	39.97	680.9	1670.000
32^4	52.14	822.4	3560.000
16^2	6.44	178.4	0.057
32^2	25.90	609.9	0.764
48^2	58.32	1224.9	3.990
64^2	103.71	2009.4	13.100
80^2	162.07	2910.7	39.400
96^2	233.40	3978.9	83.100
112^2	317.70	5080.8	148.000
128^2	414.97	6348.2	240.000
8^3	2.43	73.6	0.067
16^3	9.73	246.3	3.080
24^3	21.89	490.2	23.000
32^3	38.91	799.9	88.700
40^3	60.79	1149.0	252.000
48^3	87.54	1555.1	599.000
56^3	119.15	1967.5	1220.000
64^3	155.63	2463.6	2290.000
4^4	0.92	30.1	0.018
8^4	3.29	93.7	1.700
12^4	7.34	185.3	18.300
16^4	13.01	296.7	92.400
20^4	20.31	427.6	325.000
24^4	29.22	574.5	913.000
28^4	39.76	732.5	2150.000
32^4	51.92	892.4	4570.000

Table 1: The relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the Los Alamos method for $d = 2, 3$, and 4 using lexicographic (upper rows) or even/odd (lower rows) update.

$V = N^d$	α	τ	n_{gf}	t_{gf}
16^2	0.410	2.40	73.5	0.025
32^2	0.445	4.27	131.7	0.175
48^2	0.460	5.85	186.7	0.554
64^2	0.470	7.70	252.9	1.800
80^2	0.475	9.30	306.4	3.690
96^2	0.477	10.48	342.4	6.200
112^2	0.479	11.70	377.6	9.200
128^2	0.482	13.58	443.3	13.800
8^3	0.235	1.21	38.4	0.037
16^3	0.275	2.30	73.2	0.835
24^3	0.290	3.21	105.0	4.230
32^3	0.300	4.26	141.8	13.500
40^3	0.305	5.12	170.0	32.500
48^3	0.310	6.33	210.0	71.500
56^3	0.310	6.51	211.0	115.000
64^3	0.312	7.30	238.0	199.000
4^4	0.155	0.56	20.1	0.013
8^4	0.185	1.26	41.0	0.660
12^4	0.200	1.82	59.1	5.120
16^4	0.210	2.38	79.0	21.900
20^4	0.215	2.84	93.0	62.800
24^4	0.220	3.39	112.0	158.000
28^4	0.225	4.16	138.0	348.000
32^4	0.225	4.22	139.0	622.000
16^2	0.405	0.87	36.0	0.013
32^2	0.440	1.89	62.0	0.086
48^2	0.460	2.88	97.0	0.302
64^2	0.470	3.91	131.0	0.906
80^2	0.474	4.74	154.0	2.250
96^2	0.479	5.88	193.0	4.470
112^2	0.482	6.69	220.0	6.760
128^2	0.484	7.79	255.4	10.100
8^3	0.240	0.55	22.2	0.022
16^3	0.275	1.06	41.0	0.535
24^3	0.290	1.67	58.0	2.860
32^3	0.300	2.12	78.0	9.000
40^3	0.305	3.04	94.2	21.400
48^3	0.310	3.23	114.0	45.400
56^3	0.312	3.94	129.1	83.000
64^3	0.315	4.42	147.0	142.000
4^4	0.150	0.29	14.9	0.011
8^4	0.185	0.68	25.0	0.485
12^4	0.200	0.96	35.2	3.660
16^4	0.210	1.30	46.5	15.400
20^4	0.220	1.82	65.0	51.800
24^4	0.225	2.20	79.0	131.000
28^4	0.225	2.28	79.0	244.000
32^4	0.228	2.55	89.0	473.000

Table 2: The tuning parameter α , the relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the Cornell method for $d = 2, 3$, and 4 using lexicographic (upper rows) or even/odd (lower rows) update.

$V = N^d$	ω	τ	n_{gf}	t_{gf}
16^2	1.630	2.27	73.2	0.026
32^2	1.780	4.03	135.8	0.190
48^2	1.830	5.69	182.6	0.642
64^2	1.870	7.17	242.0	1.790
80^2	1.890	8.59	289.0	3.680
96^2	1.900	10.24	321.5	5.990
112^2	1.920	11.82	401.7	10.100
128^2	1.920	13.15	405.4	13.100
8^3	1.420	1.17	38.5	0.037
16^3	1.640	2.19	73.5	0.826
24^3	1.730	3.14	105.0	4.290
32^3	1.780	4.01	133.0	13.000
40^3	1.820	4.85	166.0	32.100
48^3	1.840	5.60	189.2	65.200
56^3	1.860	6.44	219.0	124.000
64^3	1.870	7.10	237.3	200.000
4^4	1.220	0.53	20.0	0.013
8^4	1.470	1.19	41.1	0.677
12^4	1.590	1.75	60.0	5.270
16^4	1.660	2.27	77.0	21.400
20^4	1.710	2.75	93.1	63.300
24^4	1.740	3.24	107.0	152.000
28^4	1.770	3.66	123.0	319.000
32^4	1.790	4.05	137.0	625.000
16^2	1.600	0.89	36.0	0.013
32^2	1.780	1.48	72.0	0.104
48^2	1.850	2.82	108.0	0.396
64^2	1.870	3.76	128.2	0.919
80^2	1.900	4.57	164.0	2.460
96^2	1.920	6.00	206.0	4.610
112^2	1.930	6.93	236.0	7.250
128^2	1.940	8.01	275.0	11.200
8^3	1.400	0.52	21.9	0.023
16^3	1.650	1.07	43.0	0.565
24^3	1.750	1.64	63.9	3.210
32^3	1.800	2.28	81.0	9.520
40^3	1.840	2.87	103.0	23.900
48^3	1.860	3.25	119.0	48.300
56^3	1.880	3.94	139.0	92.200
64^3	1.890	4.72	154.7	150.000
4^4	1.220	0.30	13.0	0.009
8^4	1.460	0.67	25.0	0.496
12^4	1.600	0.92	37.0	3.880
16^4	1.680	1.30	49.0	16.100
20^4	1.730	1.59	59.0	47.400
24^4	1.770	1.93	71.0	119.000
28^4	1.800	2.28	82.0	256.000
32^4	1.820	2.51	92.2	489.000

Table 3: The tuning parameter ω , the relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the overrelaxation method for $d = 2, 3$, and 4 using lexicographic (upper rows) or even/odd (lower rows) update.

$V = N^d$	p	τ	n_{gf}	t_{gf}
16^2	0.580	2.53	89.7	0.033
32^2	0.770	5.05	181.1	0.261
48^2	0.830	7.50	258.1	0.823
64^2	0.870	9.94	342.0	2.400
80^2	0.900	12.29	444.3	5.640
96^2	0.910	14.65	502.6	9.540
112^2	0.920	17.32	573.2	14.600
128^2	0.930	19.57	656.2	21.800
8^3	0.400	1.30	48.4	0.046
16^3	0.630	2.61	96.0	1.120
24^3	0.730	3.92	141.1	5.790
32^3	0.790	5.12	187.9	18.400
40^3	0.830	6.38	237.0	46.200
48^3	0.850	7.53	273.3	95.100
56^3	0.870	8.66	318.3	179.000
64^3	0.880	10.03	349.7	298.000
4^4	0.160	0.65	25.1	0.016
8^4	0.440	1.38	52.1	0.868
12^4	0.580	2.06	78.4	6.960
16^4	0.660	2.73	103.0	29.000
20^4	0.710	3.38	125.4	86.300
24^4	0.750	4.00	149.2	215.000
28^4	0.780	4.62	173.0	465.000
32^4	0.800	5.22	193.2	881.000
16^2	0.520	1.73	62.7	0.024
32^2	0.730	3.29	120.6	0.182
48^2	0.810	4.88	178.2	0.601
64^2	0.850	6.39	232.4	1.770
80^2	0.880	7.95	290.9	4.550
96^2	0.900	9.61	352.8	8.210
112^2	0.910	11.25	404.1	12.800
128^2	0.920	13.15	465.9	19.300
8^3	0.350	1.03	38.8	0.040
16^3	0.590	1.96	73.4	0.951
24^3	0.700	2.89	107.2	5.450
32^3	0.770	3.85	144.7	17.300
40^3	0.810	4.77	179.1	42.300
48^3	0.840	5.75	216.0	88.800
56^3	0.860	6.64	249.7	165.000
64^3	0.870	7.41	271.6	267.000
4^4	0.160	0.60	23.2	0.015
8^4	0.400	1.13	43.1	0.824
12^4	0.540	1.66	63.1	6.590
16^4	0.630	2.19	83.8	27.900
20^4	0.690	2.71	103.8	84.500
24^4	0.730	3.21	122.0	206.000
28^4	0.760	3.71	140.0	442.000
32^4	0.790	4.26	162.0	882.000

Table 4: The tuning parameter p , the relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the stochastic overrelaxation method for $d = 2, 3$, and 4 using lexicographic (upper rows) or even/odd (lower rows) update.

$V = N^d$	α	τ	n_{gf}	t_{gf}
16^2	1.000	0.06	5.1	0.004
32^2	1.000	0.06	5.4	0.015
64^2	1.000	0.04	6.0	0.092
128^2	1.000	0.05	6.0	0.679
8^3	1.015	0.01	6.9	0.011
16^3	1.000	0.06	5.0	0.118
32^3	1.000	0.06	5.0	2.590
64^3	1.000	0.07	5.1	30.500
4^4	1.000	0.05	5.0	0.005
8^4	1.000	0.05	5.0	0.145
16^4	1.000	0.06	5.0	6.890
32^4	1.000	0.06	5.0	136.000
16^2	1.150	0.27	11.0	0.009
32^2	1.140	0.26	11.0	0.042
64^2	1.130	0.25	10.2	0.232
128^2	1.125	0.25	10.0	2.580
8^3	1.150	0.27	11.0	0.024
16^3	1.140	0.26	10.3	0.324
32^3	1.130	0.25	10.0	8.990
64^3	1.115	0.24	10.0	109.000
4^4	1.155	0.27	11.0	0.013
8^4	1.140	0.26	10.4	0.387
16^4	1.125	0.25	10.0	24.000
32^4	1.105	0.23	9.2	443.000

Table 5: The tuning parameter α , the relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the Fourier acceleration method for $d = 2, 3$, and 4 using for the Laplacian preconditioning the whole lattice (upper rows) or even/odd sublattices (lower rows).

$V = N^2$	τ	n_{gf}	t_{gf}
16^2	16.46	378.1	0.115
32^2	65.13	1217.7	1.460
48^2	146.19	2343.3	7.310
64^2	259.68	3750.3	23.300
80^2	405.58	5209.9	61.700
96^2	583.91	7033.1	119.000
112^2	794.66	8754.2	198.000
128^2	1037.80	9996.4	292.000
16^2	16.30	392.3	0.125
32^2	64.93	1279.7	1.590
48^2	145.99	2527.7	7.060
64^2	259.47	4095.9	26.400
80^2	405.37	5799.6	80.000
96^2	583.69	7714.4	162.000
112^2	794.44	9727.4	285.000
128^2	1037.60	10001.0	383.000

Table 6: The relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the Los Alamos method for $d = 2$ using lexicographic (upper rows) or even/odd (lower rows) update with $\lambda_1 = 1$ and $\lambda_2 = 0.25$.

$V = N^2$	α	τ	n_{gf}	t_{gf}
16^2	0.680	2.71	87.1	0.029
32^2	0.730	5.14	163.6	0.217
48^2	0.750	7.42	235.6	0.708
64^2	0.760	9.61	298.9	1.920
80^2	0.767	11.67	369.9	4.670
96^2	0.772	13.86	439.0	7.940
112^2	0.775	15.57	484.5	11.700
128^2	0.777	17.44	539.4	16.700
16^2	0.685	1.60	50.0	0.018
32^2	0.740	2.95	101.0	0.140
48^2	0.755	4.68	139.4	0.437
64^2	0.767	5.82	189.0	1.280
80^2	0.772	7.22	225.3	3.380
96^2	0.777	8.64	274.0	6.130
112^2	0.780	10.05	309.6	9.550
128^2	0.782	11.41	352.9	14.100

Table 7: The tuning parameter α , the relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the Cornell method for $d = 2$ using lexicographic (upper rows) or even/odd (lower rows) update with $\lambda_1 = 1$ and $\lambda_2 = 0.25$.

$V = N^2$	ω	τ	n_{gf}	t_{gf}
16^2	1.700	2.67	90.3	0.033
32^2	1.820	5.08	165.5	0.231
48^2	1.870	7.48	236.7	0.747
64^2	1.900	9.46	310.9	2.310
80^2	1.920	11.77	391.2	4.890
96^2	1.930	13.72	449.2	8.380
112^2	1.940	15.91	525.1	13.400
128^2	1.940	18.69	531.9	17.100
16^2	1.690	0.64	62.6	0.024
32^2	1.840	2.83	98.9	0.145
48^2	1.890	4.35	145.9	0.474
64^2	1.920	5.91	200.3	1.490
80^2	1.940	7.99	267.8	3.980
96^2	1.950	9.74	321.0	7.390
112^2	1.950	10.90	329.1	10.500
128^2	1.960	12.24	400.0	16.400

Table 8: The tuning parameter ω , the relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the overrelaxation method for $d = 2$ using lexicographic (upper rows) or even/odd (lower rows) update with $\lambda_1 = 1$ and $\lambda_2 = 0.25$.

$V = N^2$	p	τ	n_{gf}	t_{gf}
16^2	0.680	3.42	121.5	0.044
32^2	0.820	6.99	239.2	0.342
48^2	0.870	10.26	346.1	1.260
64^2	0.900	13.69	455.1	3.230
80^2	0.920	16.44	569.9	7.530
96^2	0.930	20.98	668.9	12.700
112^2	0.940	23.92	779.6	19.800
128^2	0.950	26.08	923.8	30.400
16^2	0.670	2.67	95.2	0.036
32^2	0.820	5.16	185.3	0.278
48^2	0.870	7.79	277.9	1.060
64^2	0.900	10.57	375.7	3.040
80^2	0.920	12.62	446.9	6.910
96^2	0.930	16.16	525.6	12.200
112^2	0.940	18.18	603.0	19.100
128^2	0.950	19.75	703.5	29.300

Table 9: The tuning parameter p , the relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the stochastic overrelaxation method for $d = 2$ using lexicographic (upper rows) or even/odd (lower rows) update with $\lambda_1 = 1$ and $\lambda_2 = 0.25$.

$V = N^2$	α	τ	n_{gf}	t_{gf}
16^2	1.000	0.06	5.4	0.004
32^2	1.000	0.05	6.0	0.017
64^2	1.000	0.05	6.0	0.093
128^2	1.000	0.06	6.0	0.748
16^2	1.150	0.27	11.0	0.009
32^2	1.140	0.26	10.2	0.040
64^2	1.130	0.25	10.0	0.230
128^2	1.120	0.24	10.0	1.840

Table 10: The tuning parameter α , the relaxation time τ , the number of sweeps n_{gf} and the time t_{gf} (in seconds) for the Fourier acceleration method for $d = 2$ using for the Laplacian preconditioning the whole lattice (upper rows) or even/odd sublattices (lower rows) with $\lambda_1 = 1$ and $\lambda_2 = 0.25$.

Algorithm	c at finite β	c at infinite β
Los Alamos	0.217 ± 0.028	0.026 ± 0.000
Cornell	0.609 ± 0.183	0.164 ± 0.004
overrelax.	0.220 ± 0.049	0.197 ± 0.040
stoc. overr.	0.300 ± 0.047	0.152 ± 0.021
Fourier	2.851 ± 0.606	0.042 ± 0.004

Table 11: The coefficients c obtained by fits of the relaxation time τ for the five gauge-fixing algorithms in two dimensions (with lexicographic update) at finite β (from Ref. [4]) and at infinite β .